

## BSA

Anzahl Modellreihen: 20

Model	Frequency Range	Output Power $P_N$ min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0025-75</a>	4 kHz ... 250 MHz 4 ... 9 kHz 9 kHz ... 250 MHz	30 / 40 75 / 100	44.8 / 48 ±3 48.8 / 51 ±2	15 / 10 20 / 20	600	3 HU, 630 mm	16
<a href="#">BSA 0025-150</a>	4 kHz ... 250 MHz 4 ... 9 kHz 9 kHz ... 250 MHz	60 / 75 150 / 200	47.8 / 51 ±3 51.8 / 54 ±2	20 / 12 20 / 20	700	3 HU, 630 mm	20
Model	Frequency Range	Output Power $P_N$ min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0040-75</a>	4 kHz ... 400 MHz 4 ... 9 kHz 9 kHz ... 400 MHz	30 / 40 75 / 100	44.8 / 48 ±3 48.8 / 51 ±2	15 / 10 25 / 20	700	3 HU, 630 mm	21
<a href="#">BSA 0040-150</a>	4 kHz ... 400 MHz 4 ... 9 kHz 9 kHz ... 400 MHz	60 / 75 150 / 200	47.8 / 51 ±3 51.8 / 54 ±2	20 / 12 25 / 20	1000	3 HU, 630 mm	22
Model	Frequency Range	Output Power $P_N$ min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0110-100</a>	9 kHz ... 100 MHz	100 / 125	50 / 52 ±2	25 / 20	440	2 HU, 430 mm	13
<a href="#">BSA 0110-125</a>	9 kHz ... 100 MHz	125 / 150	51 / 53 ±2	20 / 20	550	2 HU, 430 mm	13
<a href="#">BSA 0110-150</a>	9 kHz ... 100 MHz	150 / 175	51.8 / 54 ±2	20 / 20	600	3 HU, 630 mm	17
<a href="#">BSA 0110-200</a>	9 kHz ... 100 MHz	200 / 230	53 / 55 ±2	20 / 20	800	3 HU, 630 mm	27
<a href="#">BSA 0110-250</a>	9 kHz ... 100 MHz	250 / 300	54 / 56 ±2	25 / 18	900	3 HU, 630 mm	28
<a href="#">BSA 0110-400</a>	9 kHz ... 100 MHz	400 / 440	56 / 58 ±2	20 / 20	2500	5 HU, 630 mm	56
<a href="#">BSA 0110-500</a>	9 kHz ... 100 MHz	500 / 600	57 / 59 ±2	20 / 20	2500	5 HU, 630 mm	56
<a href="#">BSA 0110-600</a>	9 kHz ... 100 MHz	600 / 700	57.8 / 60 ±2	20 / 20	2500	5 HU, 630 mm	58
<a href="#">BSA 0110-1000</a>	9 kHz ... 100 MHz	1000 / 1200	60 / 62 ±2	20 / 20	4000	10 HU, 630 mm	95
<a href="#">BSA 0110-1500</a>	9 kHz ... 100 MHz	1500 / 1700	61.8 / 64 ±2	20 / 20	10000	24 HU, 800 mm	290
Model	Frequency Range	Output Power $P_N$ min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0122-5000/4000</a>	9 kHz ... 220 MHz 9 kHz ... 100 MHz 100 ... 220 MHz	5000 / 5500 4000 / 4400	67 / 70 ±3 67 / 70 ±3	20 / 20 20 / 20	35000	41 HU, 800 mm	600
<a href="#">BSA 0122-10000/8000</a>	9 kHz ... 220 MHz 9 kHz ... 100 MHz 100 ... 220 MHz	10000 / 11000 8000 / 8800	70 / 73 ±3 70 / 73 ±3	20 / 20 20 / 20	55000	2x 41 HU, 1100 mm	900
Model	Frequency Range	Output Power $P_N$ min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0125-5</a>	9 kHz ... 250 MHz	5 / 8	37 / 39 ±2	20 / 20	100	2 HU, 430 mm	10
<a href="#">BSA 0125-15</a>	9 kHz ... 250 MHz	15 / 25	41.8 / 44 ±2	20 / 20	175	2 HU, 430 mm	10
<a href="#">BSA 0125-25</a>	9 kHz ... 250 MHz	25 / 30	44 / 46 ±2	20 / 20	200	2 HU, 430 mm	10
<a href="#">BSA 0125-75</a>	9 kHz ... 250 MHz	75 / 100	48.8 / 51 ±2	25 / 20	350	2 HU, 430 mm	13
<a href="#">BSA 0125-125</a>	9 kHz ... 250 MHz	125 / 150	51 / 53 ±2	25 / 20	600	3 HU, 630 mm	18
<a href="#">BSA 0125-150</a>	9 kHz ... 250 MHz	150 / 200	51.8 / 54 ±2	20 / 20	650	3 HU, 630 mm	27
<a href="#">BSA 0125-200</a>	9 kHz ... 250 MHz	200 / 220	53 / 55 ±2	20 / 20	1150	3 HU, 630 mm	30
<a href="#">BSA 0125-250</a>	9 kHz ... 250 MHz	250 / 300	54 / 56 ±2	20 / 20	1300	3 HU, 630 mm	31
<a href="#">BSA 0125-300N</a>	9 kHz ... 250 MHz	300 / 350	54 / 56 ±2	20 / 20	850	3 HU, 630 mm	34
<a href="#">BSA 0125-400</a>	9 kHz ... 250 MHz	400 / 500	56 / 58 ±2	20 / 20	2000	5 HU, 630 mm	52
<a href="#">BSA 0125-500</a>	9 kHz ... 250 MHz	500 / 600	57 / 59 ±2	20 / 20	2800	5 HU, 630 mm	58
<a href="#">BSA 0125-800</a>	9 kHz ... 250 MHz	800 / 900	59 / 61 ±2	20 / 20	5000	10 HU, 630 mm	110
<a href="#">BSA 0125-1000/800</a>	9 kHz ... 250 MHz 9 kHz ... 200 MHz 200 ... 250 MHz	1000 / 1200 800 / 1000	60 / 62 ±2 59 / 61 ±2	20 / 18 20 / 20	6000	10 HU, 630 mm	110
<a href="#">BSA 0125-1000</a>	9 kHz ... 250 MHz	1000 / 1100	60 / 62 ±2	20 / 18	7000	10 HU, 630 mm	110
Model	Frequency Range	Output Power $P_N$ min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0140-5</a>	9 kHz ... 400 MHz	5 / 8	37 / 39 ±2	20 / 20	100	2 HU, 430 mm	10
<a href="#">BSA 0140-10</a>	9 kHz ... 400 MHz	10 / 15	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	12
<a href="#">BSA 0140-20</a>	9 kHz ... 400 MHz	20 / 25	43 / 45 ±2	20 / 20	180	2 HU, 430 mm	13
<a href="#">BSA 0140-40</a>	9 kHz ... 400 MHz	40 / 50	46 / 48 ±2	20 / 20	350	2 HU, 430 mm	13
<a href="#">BSA 0140-75</a>	9 kHz ... 400 MHz	75 / 100	48.8 / 51 ±2	20 / 20	600	3 HU, 630 mm	22
<a href="#">BSA 0140-100</a>	9 kHz ... 400 MHz	100 / 120	50 / 52 ±2	25 / 20	800	3 HU, 630 mm	17
<a href="#">BSA 0140-150</a>	9 kHz ... 400 MHz	150 / 200	51.8 / 54 ±2	20 / 20	850	3 HU, 630 mm	17
<a href="#">BSA 0140-200</a>	9 kHz ... 400 MHz	200 / 250	53 / 55 ±2	20 / 20	1250	4 HU, 630 mm	35
<a href="#">BSA 0140-250</a>	9 kHz ... 400 MHz	250 / 280	54 / 56 ±2	25 / 20	1800	4 HU, 630 mm	38
<a href="#">BSA 0140-400</a>	9 kHz ... 400 MHz	400 / 450	56 / 58 ±2	20 / 20	3100	5 HU, 630 mm	59
<a href="#">BSA 0140-500/250</a>	9 kHz ... 400 MHz 9 kHz ... 250 MHz 250 ... 400 MHz	500 / 600 250 / 300	57 / 59 ±2 54 / 56 ±2	20 / 20 20 / 20	2500	5 HU, 630 mm	58

<a href="#">BSA 0140-500D</a>	9 kHz ... 400 MHz 9 kHz ... 100 MHz 100 ... 400 MHz	500 / 600 500 / 600	57 / 59 ±2 57 / 59 ±2	20 / 20 20 / 20	2800	9 HU, 630 mm	85
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0150-5</a>	9 kHz ... 500 MHz	5 / 8	37 / 39 ±2	20 / 20	100	2 HU, 430 mm	11
<a href="#">BSA 0150-10</a>	9 kHz ... 500 MHz	10 / 12	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	12
<a href="#">BSA 0150-30</a>	9 kHz ... 500 MHz	30 / 35	44.8 / 47 ±2	20 / 20	320	2 HU, 430 mm	13
<a href="#">BSA 0150-50</a>	9 kHz ... 500 MHz	50 / 70	47 / 49 ±2	20 / 20	400	3 HU, 630 mm	20
<a href="#">BSA 0150-75</a>	9 kHz ... 500 MHz	75 / 90	48.8 / 51 ±2	20 / 20	850	3 HU, 630 mm	26
<a href="#">BSA 0150-100</a>	9 kHz ... 500 MHz	100 / 120	50 / 52 ±2	20 / 20	900	3 HU, 630 mm	26
<a href="#">BSA 0150-150D</a>	9 kHz ... 500 MHz 9 kHz ... 250 MHz 200 ... 500 MHz	150 / 180 150 / 180	51.8 / 54 ±2 51.8 / 54 ±2	20 / 18 20 / 20	900	5 HU, 630 mm	44
<a href="#">BSA 0150-500D</a>	9 kHz ... 500 MHz 9 kHz ... 250 MHz 200 ... 500 MHz	500 / 600 500 / 600	57 / 59 ±2 57 / 59 ±2	20 / 20 20 / 20	2800	9 HU, 630 mm	85
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0101-5</a>	9 kHz ... 1000 MHz	5 / 8	37 / 39 ±2	20 / 20	100	2 HU, 430 mm	11
<a href="#">BSA 0101-7.5</a>	9 kHz ... 1000 MHz	7.5 / 10	38.8 / 41 ±2	20 / 20	150	2 HU, 430 mm	13
<a href="#">BSA 0101-25/30D</a>	9 kHz ... 1000 MHz 9 kHz ... 250 MHz 200 ... 1000 MHz	25 / 30 30 / 35	44 / 46 ±2 44.8 / 47 ±2	25 / 20 25 / 25	450	2 HU, 430 mm	14
<a href="#">BSA 0101-75/60D</a>	9 kHz ... 1000 MHz 9 kHz ... 250 MHz 200 ... 1000 MHz	75 / 100 60 / 75	48.8 / 51 ±2 47.8 / 50 ±2	20 / 20 20 / 20	450	3 HU, 630 mm	24
<a href="#">BSA 0101-100D</a>	9 kHz ... 1000 MHz 9 kHz ... 400 MHz 400 ... 1000 MHz	100 / 120 100 / 120	50 / 52 ±2 50 / 52 ±2	25 / 20 25 / 20	680	3 HU, 630 mm	24
<a href="#">BSA 0101-150/120D</a>	9 kHz ... 1000 MHz 9 kHz ... 400 MHz 400 ... 1000 MHz	150 / 180 120 / 130	51.8 / 54 ±2 50.8 / 53 ±2	25 / 20 20 / 20	1050	4 HU, 630 mm	38
<a href="#">BSA 0101-250/120D</a>	9 kHz ... 1000 MHz 9 kHz ... 250 MHz 200 ... 1000 MHz	250 / 280 120 / 140	54 / 56 ±2 50.8 / 53 ±2	20 / 18 20 / 20	1400	4 HU, 630 mm	41
<a href="#">BSA 0101-250D</a>	9 kHz ... 1000 MHz 9 kHz ... 400 MHz 400 ... 1000 MHz	250 / 300 250 / 300	54 / 56 ±2 54 / 56 ±2	20 / 20 20 / 20	2100	4 HU, 630 mm	43
<a href="#">BSA 0101-500D</a>	9 kHz ... 1000 MHz 9 kHz ... 250 MHz 200 ... 1000 MHz	500 / 600 500 / 600	57 / 59 ±2 57 / 59 ±2	20 / 20 20 / 20	4000	9 HU, 630 mm	85
<a href="#">BSA 0101-1000D</a>	9 kHz ... 1000 MHz 9 kHz ... 100 MHz 100 ... 1000 MHz	1000 / 1200 1000 / 1200	60 / 62 ±2 60 / 62 ±2	20 / 18 20 / 20	9000	32 HU, 800 mm	300
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0102-25/20D</a>	9 kHz ... 2500 MHz 9 kHz ... 500 MHz 500 ... 2500 MHz	25 / 30 20 / 25	44 / 46 ±2 43 / 46 ±3	20 / 20 15 / 15	250	2 HU, 430 mm	20
<a href="#">BSA 0102-50D</a>	9 kHz ... 2500 MHz 9 kHz ... 500 MHz 500 ... 2500 MHz	50 / 60 50 / 60	47 / 49 ±2 47 / 49 ±2	20 / 20 15 / 20	550	3 HU, 630 mm	25
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0103-25/20D</a>	9 kHz ... 3000 MHz 9 kHz ... 250 MHz 200 ... 1000 MHz 1000 ... 3000 MHz	25 / 30 25 / 30 20 / 25	44 / 46 ±2 44 / 46 ±2 43 / 46 ±3	20 / 20 20 / 20 15 / 20	250	3 HU, 630 mm	30
<a href="#">BSA 0103-40/30/20D</a>	9 kHz ... 3000 MHz 9 kHz ... 250 MHz 200 ... 1000 MHz 1000 ... 3000 MHz	40 / 50 30 / 40 20 / 25	46 / 48 ±2 44.8 / 47 ±2 43 / 46 ±3	20 / 20 20 / 20 15 / 20	400	3 HU, 630 mm	25
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 0106-25/10D</a>	9 kHz ... 6000 MHz 9 kHz ... 250 MHz 200 ... 1000 MHz 1000 ... 6000 MHz	25 / 30 25 / 30 10 / 15	44 / 46 ±2 44 / 46 ±2 40 / 43 ±3	20 / 20 20 / 20 15 / 20	200	3 HU, 430 mm	24
<a href="#">BSA 0106-25D</a>	9 kHz ... 6000 MHz 9 kHz ... 250 MHz 200 ... 1000 MHz 1000 ... 6000 MHz	25 / 30 25 / 30 25 / 30	44 / 46 ±2 44 / 46 ±2 44 / 47 ±3	20 / 20 20 / 20 15 / 20	250	3 HU, 630 mm	26
<a href="#">BSA 0106-75D</a>	9 kHz ... 6000 MHz 9 kHz ... 400 MHz 400 ... 1000 MHz 1000 ... 6000 MHz	75 / 85 75 / 85 75 / 85	48.8 / 51 ±2 48.8 / 51 ±2 48.8 / 52 ±3	20 / 20 20 / 20 15 / 20	1000	3 HU, 630 mm	32
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg

<a href="#">BSA 1010-10</a>	100 kHz ... 100 MHz	10 / 15	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	12
<a href="#">BSA 1010-30</a>	100 kHz ... 100 MHz	30 / 35	44.8 / 47 ±2	20 / 20	350	2 HU, 430 mm	13
<a href="#">BSA 1010-50</a>	100 kHz ... 100 MHz	50 / 70	47 / 49 ±2	20 / 18	380	2 HU, 430 mm	13
<a href="#">BSA 1010-125</a>	100 kHz ... 100 MHz	125 / 140	51 / 53 ±2	20 / 20	550	2 HU, 430 mm	13
<a href="#">BSA 1010-150</a>	100 kHz ... 100 MHz	150 / 200	51.8 / 54 ±2	20 / 20	600	3 HU, 630 mm	17
<a href="#">BSA 1010-250</a>	100 kHz ... 100 MHz	250 / 280	54 / 56 ±2	20 / 20	900	3 HU, 630 mm	29
<a href="#">BSA 1010-500</a>	100 kHz ... 100 MHz	500 / 600	57 / 59 ±2	20 / 20	2800	5 HU, 630 mm	45
<a href="#">BSA 1010-600</a>	100 kHz ... 100 MHz	600 / 750	57.8 / 60 ±2	20 / 20	3000	5 HU, 630 mm	45
<a href="#">BSA 1010-1000</a>	100 kHz ... 100 MHz	1000 / 1700	60 / 62 ±2	20 / 20	5500	15 HU, 630 mm	140
<a href="#">BSA 1010-1200</a>	100 kHz ... 100 MHz	1200 / 1300	60.8 / 63 ±2	20 / 20	6000	18 HU, 800 mm	175
<a href="#">BSA 1010-1500</a>	100 kHz ... 100 MHz	1500 / 1700	61.8 / 64 ±2	20 / 20	10000	24 HU, 800 mm	290

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 1025-40</a>	100 kHz ... 250 MHz	40 / 45	46 / 48 ±2	25 / 20	350	2 HU, 430 mm	13
<a href="#">BSA 1025-100</a>	100 kHz ... 250 MHz	100 / 110	50 / 52 ±2	20 / 20	500	2 HU, 430 mm	13
<a href="#">BSA 1025-150</a>	100 kHz ... 250 MHz	150 / 170	51.8 / 54 ±2	20 / 20	600	3 HU, 630 mm	21
<a href="#">BSA 1025-200</a>	100 kHz ... 250 MHz	200 / 240	53 / 55 ±2	20 / 20	800	3 HU, 630 mm	29
<a href="#">BSA 1025-250</a>	100 kHz ... 250 MHz	250 / 280	54 / 56 ±2	20 / 20	1200	3 HU, 630 mm	30
<a href="#">BSA 1025-400</a>	100 kHz ... 250 MHz	400 / 450	56 / 58 ±2	20 / 20	2250	5 HU, 630 mm	46
<a href="#">BSA 1025-500</a>	100 kHz ... 250 MHz	500 / 600	57 / 59 ±2	20 / 20	2300	5 HU, 630 mm	52
<a href="#">BSA 1025-1000</a>	100 kHz ... 250 MHz	1000 / 1100	60 / 62 ±2	20 / 20	6000	18 HU, 800 mm	200

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 1040-50</a>	100 kHz ... 400 MHz	50 / 70	47 / 49 ±2	20 / 20	400	2 HU, 430 mm	13
<a href="#">BSA 1040-100</a>	100 kHz ... 400 MHz	100 / 120	50 / 52 ±2	20 / 20	550	2 HU, 430 mm	13
<a href="#">BSA 1040-250/150</a>	100 kHz ... 400 MHz 100 kHz ... 100 MHz 100 ... 400 MHz	250 / 300 150 / 180	54 / 56 ±2 51.8 / 54 ±2	20 / 20 20 / 20	1200	3 HU, 630 mm	32
<a href="#">BSA 1040-300</a>	100 kHz ... 400 MHz	300 / 330	54.8 / 57 ±2	20 / 20	1700	5 HU, 630 mm	42
<a href="#">BSA 1040-500/400</a>	100 kHz ... 400 MHz 100 kHz ... 300 MHz 300 ... 400 MHz	500 / 600 400 / 450	57 / 59 ±2 56 / 58 ±2	25 / 20 25 / 20	2500	5 HU, 630 mm	41
<a href="#">BSA 1040-600/350</a>	100 kHz ... 400 MHz 100 kHz ... 100 MHz 100 ... 250 MHz 250 ... 400 MHz	600 / 700 500 / 600 350 / 400	57.8 / 60 ±2 57 / 59 ±2 55.4 / 57 ±2	20 / 20 20 / 20 20 / 20	2800	5 HU, 630 mm	45

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 1050-50</a>	100 kHz ... 500 MHz	50 / 70	47 / 49 ±2	20 / 20	600	3 HU, 630 mm	21
<a href="#">BSA 1050-100</a>	100 kHz ... 500 MHz	100 / 120	50 / 52 ±2	20 / 20	1200	3 HU, 630 mm	30
<a href="#">BSA 1050-300/100</a>	100 kHz ... 500 MHz 100 kHz ... 400 MHz 400 ... 500 MHz	300 / 350 100 / 150	54.8 / 57 ±2 50 / 52 ±2	20 / 20 20 / 20	2200	4 HU, 630 mm	40
<a href="#">BSA 1050-500/100</a>	100 kHz ... 500 MHz 100 kHz ... 250 MHz 250 ... 400 MHz 400 ... 500 MHz	500 / 600 300 / 350 100 / 120	57 / 59 ±2 54.8 / 57 ±2 53 / 55 ±2	20 / 20 20 / 20 20 / 20	2500	5 HU, 630 mm	45

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 1001-30D</a>	100 kHz ... 1000 MHz 100 kHz ... 100 MHz 100 ... 1000 MHz	30 / 35 30 / 35	44.8 / 47 ±2 44.8 / 47 ±2	25 / 20 25 / 20	360	2 HU, 430 mm	15
<a href="#">BSA 1001-50/75D</a>	100 kHz ... 1000 MHz 100 kHz ... 400 MHz 400 ... 1000 MHz	50 / 70 75 / 100	47 / 49 ±2 48.8 / 51 ±2	20 / 20 20 / 20	600	3 HU, 630 mm	26
<a href="#">BSA 1001-75D</a>	100 kHz ... 1000 MHz 100 kHz ... 400 MHz 400 ... 1000 MHz	75 / 100 75 / 100	48.8 / 51 ±2 48.8 / 51 ±2	20 / 20 20 / 20	600	3 HU, 630 mm	26
<a href="#">BSA 1001-100D</a>	100 kHz ... 1000 MHz 100 kHz ... 400 MHz 400 ... 1000 MHz	100 / 120 100 / 120	50 / 52 ±2 50 / 52 ±2	20 / 20 20 / 20	550	3 HU, 630 mm	25
<a href="#">BSA 1001-150/125D</a>	100 kHz ... 1000 MHz 100 kHz ... 400 MHz 400 ... 1000 MHz	150 / 170 125 / 140	51.8 / 54 ±2 51 / 53 ±2	20 / 20 20 / 20	900	3 HU, 630 mm	35
<a href="#">BSA 1001-250D</a>	100 kHz ... 1000 MHz 100 kHz ... 400 MHz 400 ... 1000 MHz	250 / 300 250 / 300	54 / 56 ±2 54 / 56 ±2	20 / 20 20 / 20	2100	4 HU, 630 mm	43
<a href="#">BSA 1001-300/250D</a>	100 kHz ... 1000 MHz 100 kHz ... 400 MHz 400 ... 1000 MHz	300 / 350 250 / 300	54.8 / 57 ±2 54 / 56 ±2	20 / 20 20 / 20	2000	8 HU, 630 mm	81
<a href="#">BSA 1001-500/300D</a>	100 kHz ... 1000 MHz 100 kHz ... 250 MHz 250 ... 400 MHz 400 ... 1000 MHz	500 / 550 300 / 350 300 / 350	57 / 59 ±2 54.8 / 57 ±2 54.8 / 57 ±2	20 / 20 20 / 20 20 / 20	2200	8 HU, 630 mm	81

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 1515-25</a>	150 kHz ... 150 MHz	25 / 35	44 / 46 ±2	25 / 20	350	2 HU, 430 mm	13

Model	Frequency Range	Output Power $P_N$ min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BSA 1515-50</a>	150 kHz ... 150 MHz	50 / 75	47 / 49 ±2	20 / 20	350	2 HU, 430 mm	14
<a href="#">BSA 1501-1</a>	150 kHz ... 1000 MHz	1 / 1.5	30 / 32 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BSA 1501-5</a>	150 kHz ... 1000 MHz	5 / 7	37 / 39 ±2	20 / 20	100	2 HU, 430 mm	11
<a href="#">BSA 1501-10</a>	150 kHz ... 1000 MHz	10 / 12	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	12
<a href="#">BSA 1503-10D</a>	150 kHz ... 3000 MHz 150 kHz ... 1000 MHz 1000 ... 3000 MHz	10 / 12 10 / 13	40 / 42 ±2 40 / 43 ±3	20 / 20 15 / 20	200	2 HU, 430 mm	14
<a href="#">BSA 5001-1</a>	500 kHz ... 1000 MHz	1 / 1.5	30 / 32 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BSA 5001-2</a>	500 kHz ... 1000 MHz	2 / 2.5	33 / 35 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BSA 5001-5</a>	500 kHz ... 1000 MHz	5 / 7	37 / 39 ±2	18 / 20	100	2 HU, 430 mm	11
<a href="#">BSA 5001-10</a>	500 kHz ... 1000 MHz	10 / 12	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	12

**BTA**

Anzahl Modellreihen: 1

Model	Frequency Range	Output Power $P_N$ min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BTA 0122-2000</a>	9 kHz ... 220 MHz	2000 / 2200	63 / 66 ±3	12 / 18	15000	18 HU, 800 mm	220
<a href="#">BTA 0122-3000</a>	9 kHz ... 220 MHz	3000 / 3300	64.8 / 67.5 ±2.5	12 / 18	25000	32 HU, 800 mm	325

**BLWA**

Anzahl Modellreihen: 30

Model	Frequency Range	Output Power $P_N$ min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0150-2</a>	1 ... 500 MHz	2 / 2.5	33 / 35 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLWA 0150-5</a>	1 ... 500 MHz	5 / 6	37 / 39 ±2	20 / 20	100	2 HU, 430 mm	11
<a href="#">BLWA 0150-10</a>	1 ... 500 MHz	10 / 12	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	12
<a href="#">BLWA 0150-25</a>	1 ... 500 MHz	25 / 30	44 / 46 ±2	20 / 20	180	2 HU, 430 mm	13
<a href="#">BLWA 0150-50</a>	1 ... 500 MHz	50 / 60	47 / 49 ±2	20 / 20	300	3 HU, 630 mm	18
<a href="#">BLWA 0110-1</a>	1 ... 1000 MHz	1 / 1.5	30 / 32 ±2	20 / 20	120	2 HU, 430 mm	10
<a href="#">BLWA 0110-3</a>	1 ... 1000 MHz	3 / 3.5	34.8 / 37 ±2	20 / 20	140	2 HU, 430 mm	10
<a href="#">BLWA 0110-5</a>	1 ... 1000 MHz	5 / 6	37 / 39 ±2	20 / 20	150	2 HU, 430 mm	10
<a href="#">BLWA 0110-10</a>	1 ... 1000 MHz	10 / 12	40 / 42 ±2	25 / 25	270	2 HU, 430 mm	9
<a href="#">BLWA 0110-15</a>	1 ... 1000 MHz	15 / 20	41.8 / 44 ±2	20 / 20	300	2 HU, 430 mm	10
<a href="#">BLWA 0110-30</a>	1 ... 1000 MHz	30 / 50	44.8 / 47 ±2	20 / 12	300	2 HU, 430 mm	14
<a href="#">BLWA 0110-60</a>	1 ... 1000 MHz	60 / 90	47.8 / 50 ±2	20 / 15	600	3 HU, 430 mm	17
<a href="#">BLWA 0110-100</a>	1 ... 1000 MHz	100 / 130	50 / 52 ±2	20 / 20	1500	5 HU, 630 mm	35
<a href="#">BLWA 0120-10D</a>	1 ... 2000 MHz 1 ... 500 MHz 500 ... 2000 MHz	10 / 12 10 / 12	40 / 42 ±2 40 / 43 ±3	20 / 20 15 / 20	250	2 HU, 430 mm	13
<a href="#">BLWA 0103-100</a>	1.5 ... 30 MHz	100 / 120	50 / 52 ±2	20 / 20	450	3 HU, 430 mm	16
<a href="#">BLWA 0103-250</a>	1.5 ... 30 MHz	250 / 300	54 / 56 ±2	20 / 18	800	3 HU, 630 mm	22
<a href="#">BLWA 0103-500</a>	1.5 ... 30 MHz	500 / 600	57 / 59 ±2	20 / 12	2000	3 HU, 630 mm	35
<a href="#">BLWA 0103-1000</a>	1.5 ... 30 MHz	1000 / 1200	60 / 62 ±2	20 / 12	4500	7 HU, 630 mm	80
<a href="#">BLWA 0103-1500</a>	1.5 ... 30 MHz	1500 / 2200	61.8 / 64 ±2	20 / 12	5000	7 HU, 630 mm	100
<a href="#">BLWA 0103-3000</a>	1.5 ... 30 MHz	3000 / 4000	64.8 / 67 ±2	20 / 12	10000	12 HU, 800 mm	200
<a href="#">BLWA 0103-5000</a>	1.5 ... 30 MHz	5000 / 6000	67 / 69 ±2	20 / 12	20000	32 HU, 800 mm	400
<a href="#">BLWA 0103-10000</a>	1.5 ... 30 MHz	10000 / 12000	70 / 72 ±2	20 / 12	40000	2x 32 HU, 800 mm	800
<a href="#">BLWA 0103-20000</a>	1.5 ... 30 MHz	20000 / 22000	73 / 75 ±2	20 / 12	80000	4x 32 HU, 800 mm	1600
<a href="#">BLWA 0303-1000</a>	3 ... 30 MHz	1000 / 1200	60 / 62 ±2	20 / 10	3000	4 HU, 630 mm	38
<a href="#">BLWA 0160-2</a>	10 ... 6000 MHz	2 / 2.2	33 / 36 ±3	15 / 20	200	2 HU, 430 mm	10
<a href="#">BLWA 0210-100</a>	20 ... 100 MHz	100 / 120	50 / 52 ±2	20 / 15	450	3 HU, 630 mm	20
<a href="#">BLWA 0210-200</a>	20 ... 100 MHz	200 / 250	53 / 55 ±2	20 / 15	800	3 HU, 630 mm	30

<a href="#">BLWA 0210-500</a>	20 ... 100 MHz	500 / 600	57 / 59 ±2	20 / 15	1800	4 HU, 630 mm	35
<a href="#">BLWA 0210-1000</a>	20 ... 100 MHz	1000 / 1200	60 / 62 ±2	20 / 15	4000	9 HU, 630 mm	80
<a href="#">BLWA 0210-1250</a>	20 ... 100 MHz	1250 / 1400	61 / 63 ±2	20 / 15	5000	9 HU, 630 mm	100
<a href="#">BLWA 0210-1800</a>	20 ... 100 MHz	1800 / 2000	62.5 / 65 ±2	20 / 15	7500	11 HU, 630 mm	135
<a href="#">BLWA 0210-2500</a>	20 ... 100 MHz	2500 / 2700	64 / 66 ±2	20 / 15	12000	12 HU, 800 mm	200
<a href="#">BLWA 0210-3000</a>	20 ... 100 MHz	3000 / 3300	64.8 / 67 ±2	20 / 15	20000	18 HU, 800 mm	300
<a href="#">BLWA 0210-4000</a>	20 ... 100 MHz	4000 / 4500	66 / 68 ±2	20 / 15	23000	24 HU, 800 mm	400
<a href="#">BLWA 0210-5000</a>	20 ... 100 MHz	5000 / 5500	67 / 69 ±2	20 / 15	30000	37 HU, 800 mm	460
<a href="#">BLWA 0210-7000</a>	20 ... 100 MHz	7000 / 8000	68.4 / 71 ±2	20 / 15	35000	2x 32 HU, 800 mm	590
<a href="#">BLWA 0210-10000</a>	20 ... 100 MHz	10000 / 11000	70 / 72 ±2	20 / 12	50000	2x 37 HU, 800 mm	1000

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0211-100</a>	20 ... 110 MHz	100 / 120	50 / 52 ±2	20 / 15	450	3 HU, 630 mm	20
<a href="#">BLWA 0211-200</a>	20 ... 110 MHz	200 / 250	53 / 55 ±2	20 / 15	800	3 HU, 630 mm	30
<a href="#">BLWA 0211-500</a>	20 ... 110 MHz	500 / 600	57 / 59 ±2	20 / 15	1800	4 HU, 630 mm	35
<a href="#">BLWA 0211-1000</a>	20 ... 110 MHz	1000 / 1200	60 / 62 ±2	20 / 15	4000	9 HU, 630 mm	80
<a href="#">BLWA 0211-1250</a>	20 ... 110 MHz	1250 / 1400	61 / 63 ±2	20 / 15	5000	9 HU, 630 mm	100
<a href="#">BLWA 0211-1800</a>	20 ... 110 MHz	1800 / 2000	62.5 / 65 ±2	20 / 15	7500	11 HU, 630 mm	135
<a href="#">BLWA 0211-2500</a>	20 ... 110 MHz	2500 / 2700	64 / 66 ±2	20 / 15	12000	12 HU, 800 mm	200
<a href="#">BLWA 0211-3000</a>	20 ... 110 MHz	3000 / 3300	64.8 / 67 ±2	20 / 15	20000	18 HU, 800 mm	300
<a href="#">BLWA 0211-4000</a>	20 ... 110 MHz	4000 / 4500	66 / 68 ±2	20 / 15	23000	24 HU, 800 mm	400
<a href="#">BLWA 0211-5000</a>	20 ... 110 MHz	5000 / 5500	67 / 69 ±2	20 / 15	30000	37 HU, 800 mm	460
<a href="#">BLWA 0211-7000</a>	20 ... 110 MHz	7000 / 8000	68.4 / 71 ±2	20 / 15	35000	2x 32 HU, 800 mm	590
<a href="#">BLWA 0211-10000</a>	20 ... 110 MHz	10000 / 11000	70 / 72 ±2	20 / 12	60000	2x 37 HU, 800 mm	1000

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0213-100</a>	20 ... 130 MHz	100 / 120	50 / 52 ±2	20 / 15	450	3 HU, 630 mm	20
<a href="#">BLWA 0213-200</a>	20 ... 130 MHz	200 / 250	53 / 55 ±2	20 / 15	800	3 HU, 630 mm	30
<a href="#">BLWA 0213-500</a>	20 ... 130 MHz	500 / 600	57 / 59 ±2	20 / 15	1800	4 HU, 630 mm	35
<a href="#">BLWA 0213-1000</a>	20 ... 130 MHz	1000 / 1200	60 / 62 ±2	20 / 15	5000	8 HU, 630 mm	100
<a href="#">BLWA 0213-1250</a>	20 ... 130 MHz	1250 / 1400	61 / 63 ±2	20 / 15	7500	8 HU, 630 mm	150
<a href="#">BLWA 0213-1800</a>	20 ... 130 MHz	1800 / 2000	62.5 / 65 ±2	20 / 15	12000	12 HU, 800 mm	200
<a href="#">BLWA 0213-2500</a>	20 ... 130 MHz	2500 / 2700	64 / 66 ±2	20 / 15	12000	12 HU, 800 mm	200
<a href="#">BLWA 0213-3000</a>	20 ... 130 MHz	3000 / 3300	64.8 / 67 ±2	20 / 15	20000	18 HU, 800 mm	300
<a href="#">BLWA 0213-4000</a>	20 ... 130 MHz	4000 / 4500	66 / 68 ±2	20 / 15	23000	24 HU, 800 mm	400
<a href="#">BLWA 0213-5000</a>	20 ... 130 MHz	5000 / 5500	67 / 69 ±2	20 / 15	30000	37 HU, 800 mm	460
<a href="#">BLWA 0213-7000</a>	20 ... 130 MHz	7000 / 8000	68.4 / 71 ±2	20 / 15	35000	2x 32 HU, 800 mm	590
<a href="#">BLWA 0213-10000</a>	20 ... 130 MHz	10000 / 11000	70 / 72 ±2	20 / 12	50000	2x 37 HU, 800 mm	1000

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0250-15</a>	20 ... 500 MHz	15 / 18	41.8 / 44 ±2	20 / 15	250	2 HU, 430 mm	12
<a href="#">BLWA 0250-35</a>	20 ... 500 MHz	35 / 40	45.4 / 48 ±2	20 / 20	280	2 HU, 430 mm	13
<a href="#">BLWA 0250-60</a>	20 ... 500 MHz	60 / 70	47.8 / 50 ±2	20 / 15	350	2 HU, 430 mm	13
<a href="#">BLWA 0250-85</a>	20 ... 500 MHz	85 / 100	49.3 / 52 ±2	20 / 15	500	3 HU, 630 mm	30
<a href="#">BLWA 0250-125</a>	20 ... 500 MHz	125 / 135	51 / 53 ±2	20 / 15	1000	3 HU, 630 mm	35
<a href="#">BLWA 0250-250</a>	20 ... 500 MHz	250 / 300	54 / 56 ±2	15 / 20	1250	5 HU, 630 mm	40
<a href="#">BLWA 0250-500</a>	20 ... 500 MHz	500 / 600	57 / 59 ±2	15 / 20	2500	5 HU, 630 mm	45
<a href="#">BLWA 0250-700</a>	20 ... 500 MHz	700 / 800	58.4 / 61 ±2	15 / 20	3500	5 HU, 630 mm	50
<a href="#">BLWA 0250-1000</a>	20 ... 500 MHz	1000 / 1200	60 / 62 ±2	15 / 20	5000	8 HU, 630 mm	75

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0210-1</a>	20 ... 1000 MHz	1 / 1.5	30 / 32 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLWA 0210-3</a>	20 ... 1000 MHz	3 / 3.5	34.8 / 37 ±2	20 / 20	100	2 HU, 430 mm	11
<a href="#">BLWA 0210-5</a>	20 ... 1000 MHz	5 / 6	37 / 39 ±2	20 / 20	150	2 HU, 430 mm	11
<a href="#">BLWA 0210-10</a>	20 ... 1000 MHz	10 / 12	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	12
<a href="#">BLWA 0210-30</a>	20 ... 1000 MHz	30 / 35	44.8 / 47 ±2	20 / 20	200	2 HU, 430 mm	13
<a href="#">BLWA 0210-40</a>	20 ... 1000 MHz	40 / 45	46 / 48 ±2	20 / 20	300	2 HU, 430 mm	14
<a href="#">BLWA 0210-50</a>	20 ... 1000 MHz	50 / 60	47 / 50 ±3	20 / 12	250	2 HU, 430 mm	13
<a href="#">BLWA 0210-100</a>	20 ... 1000 MHz	100 / 120	50 / 52 ±2	20 / 20	900	3 HU, 630 mm	26
<a href="#">BLWA 0210-150</a>	20 ... 1000 MHz	150 / 200	51.8 / 54 ±2	20 / 20	1500	5 HU, 630 mm	40
<a href="#">BLWA 0210-300</a>	20 ... 1000 MHz	300 / 330	54.8 / 57 ±2	20 / 12	1900	4 HU, 630 mm	42
<a href="#">BLWA 0210-500</a>	20 ... 1000 MHz	500 / 550	57 / 59 ±2	20 / 15	4000	8 HU, 630 mm	58
<a href="#">BLWA 0210-350/200/100D</a>	20 ... 1000 MHz 20 ... 100 MHz 100 ... 400 MHz 400 ... 1000 MHz	350 / 400 200 / 220 100 / 120	55.4 / 58 ±2 53 / 55 ±2 50 / 52 ±2	20 / 15 20 / 15 20 / 20	1000	8 HU, 630 mm	60

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0225-5</a>	20 ... 2500 MHz	5 / 7	37 / 40 ±3	12 / 15	70	2 HU, 430 mm	13
<a href="#">BLWA 0225-10</a>	20 ... 2500 MHz	10 / 12	40 / 43 ±3	12 / 15	100	2 HU, 430 mm	13

<a href="#">BLWA 0225-25/20D</a>	20 ... 2500 MHz 20 ... 500 MHz 500 ... 2500 MHz	25 / 30 20 / 25	44 / 46 ±2 43 / 45 ±2	20 / 15 15 / 15	200	3 HU, 430 mm	15
<a href="#">BLWA 0225-50D</a>	20 ... 2500 MHz 20 ... 500 MHz 500 ... 2500 MHz	50 / 60 50 / 60	57 / 60 ±3 57 / 60 ±3	20 / 15 15 / 20	400	3 HU, 430 mm	20
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0230-5D</a>	20 ... 3000 MHz 20 ... 1000 MHz 1000 ... 3000 MHz	5 / 6 5 / 6	37 / 39 ±2 37 / 40 ±3	20 / 20 15 / 20	200	2 HU, 430 mm	13
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0260-25D</a>	20 ... 6000 MHz 20 ... 1000 MHz 1000 ... 6000 MHz	25 / 30 25 / 30	44 / 46 ±2 44 / 46 ±2	20 / 20 15 / 20	500	3 HU, 430 mm	19
<a href="#">BLWA 0260-30/10D</a>	20 ... 6000 MHz 20 ... 1000 MHz 1000 ... 6000 MHz	30 / 35 10 / 13	44.8 / 47 ±2 40 / 43 ±3	20 / 20 15 / 20	320	2 HU, 430 mm	17
<a href="#">BLWA 0260-30/20/10D</a>	20 ... 6000 MHz 20 ... 1000 MHz 1 ... 2.5 GHz 2.5 ... 6 GHz	30 / 35 20 / 25 10 / 13	44.8 / 47 ±2 43 / 46 ±3 40 / 43 ±3	25 / 20 15 / 20 15 / 20	320	2 HU, 430 mm	14
<a href="#">BLWA 0260-40D</a>	20 ... 6000 MHz 20 ... 1000 MHz 1000 ... 6000 MHz	40 / 45 40 / 45	46 / 48 ±2 46 / 49 ±3	20 / 20 15 / 20	700	3 HU, 430 mm	21
<a href="#">BLWA 0260-50/25D</a>	20 ... 6000 MHz 20 ... 1000 MHz 1000 ... 6000 MHz	50 / 60 25 / 30	47 / 49 ±2 44 / 47 ±3	25 / 20 15 / 20	550	3 HU, 430 mm	17
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0240-5/3/0.8</a>	20 MHz ... 40 GHz 20 MHz ... 1000 kHz 1 ... 18 GHz 18 ... 40 GHz	5 / 6 3 / 3.3 0.8 / 0.9	37 / 39 ±2 34.8 / 39 ±4 29 / 33 ±4	20 / 20 15 / 15 7 / 15	200	3 HU, 430 mm	18
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0840-150</a>	80 ... 400 MHz	150 / 180	51.8 / 54 ±2	20 / 15	800	3 HU, 630 mm	30
<a href="#">BLWA 0840-250</a>	80 ... 400 MHz	250 / 300	54 / 56 ±2	20 / 15	1600	4 HU, 630 mm	35
<a href="#">BLWA 0840-500</a>	80 ... 400 MHz	500 / 600	57 / 59 ±2	20 / 15	3000	6 HU, 630 mm	55
<a href="#">BLWA 0840-750</a>	80 ... 400 MHz	750 / 900	58.8 / 61 ±2	20 / 15	4500	8 HU, 630 mm	120
<a href="#">BLWA 0840-1000</a>	80 ... 400 MHz	1000 / 1150	60 / 62 ±2	20 / 15	8000	16 HU, 630 mm	180
<a href="#">BLWA 0840-1500</a>	80 ... 400 MHz	1500 / 1700	61.8 / 64 ±2	20 / 15	10000	19 HU, 630 mm	200
<a href="#">BLWA 0840-2000</a>	80 ... 400 MHz	2000 / 2200	63 / 65 ±2	20 / 15	17000	41 HU, 800 mm	300
<a href="#">BLWA 0840-3000</a>	80 ... 400 MHz	3000 / 3300	64.8 / 67 ±2	20 / 15	20000	41 HU, 800 mm	400
<a href="#">BLWA 0840-4000</a>	80 ... 400 MHz	4000 / 4400	66 / 68 ±2	20 / 15	35000	2x 32 HU, 800 mm	600
<a href="#">BLWA 0840-5000</a>	80 ... 400 MHz	5000 / 5500	67 / 69 ±2	20 / 15	45000	2x 32 HU, 800 mm	800
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0850-60</a>	80 ... 500 MHz	60 / 70	47.8 / 50 ±2	20 / 18	300	2 HU, 430 mm	14
<a href="#">BLWA 0850-200</a>	80 ... 500 MHz	200 / 240	53 / 55 ±2	20 / 20	950	3 HU, 630 mm	27
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0810-10</a>	80 ... 1000 MHz	10 / 12	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	11
<a href="#">BLWA 0810-30</a>	80 ... 1000 MHz	30 / 35	44.8 / 47 ±2	20 / 20	200	2 HU, 430 mm	11
<a href="#">BLWA 0810-40</a>	80 ... 1000 MHz	40 / 45	46 / 48 ±2	20 / 20	300	2 HU, 430 mm	13
<a href="#">BLWA 0810-50</a>	80 ... 1000 MHz	50 / 60	47 / 49 ±2	20 / 20	400	3 HU, 430 mm	20
<a href="#">BLWA 0810-100</a>	80 ... 1000 MHz	100 / 120	50 / 52 ±2	20 / 20	900	3 HU, 630 mm	26
<a href="#">BLWA 0810-125</a>	80 ... 1000 MHz	125 / 140	51 / 53 ±2	25 / 25	950	3 HU, 630 mm	27
<a href="#">BLWA 0810-150</a>	80 ... 1000 MHz	150 / 160	51.8 / 54 ±2	25 / 25	1000	3 HU, 630 mm	27
<a href="#">BLWA 0810-250/150</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	250 / 280 150 / 160	54 / 56 ±2 51.8 / 54 ±2	25 / 20 25 / 20	950	3 HU, 630 mm	27
<a href="#">BLWA 0810-250</a>	80 ... 1000 MHz	250 / 300	54 / 56 ±2	25 / 20	2000	4 HU, 630 mm	38
<a href="#">BLWA 0810-400/250</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	400 / 440 250 / 300	56 / 58 ±2 54 / 56 ±2	25 / 20 25 / 25	2400	4 HU, 630 mm	39
<a href="#">BLWA 0810-400</a>	80 ... 1000 MHz	400 / 450	56 / 58 ±2	20 / 20	3100	6 HU, 630 mm	73
<a href="#">BLWA 0810-500/200D</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	500 / 600 200 / 220	57 / 59 ±2 53 / 55 ±2	20 / 15 20 / 20	3300	9 HU, 630 mm	85
<a href="#">BLWA 0810-500/350D</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	500 / 600 350 / 400	57 / 59 ±2 55.4 / 58 ±2	20 / 15 20 / 20	3300	9 HU, 630 mm	95
<a href="#">BLWA 0810-500</a>	80 ... 1000 MHz	500 / 600	57 / 59 ±2	20 / 20	4000	6 HU, 630 mm	70
<a href="#">BLWA 0810-750</a>	80 ... 1000 MHz	750 / 800	58.8 / 61 ±2	20 / 20	7000	18 HU, 800 mm	250



<a href="#">BLWA 0810-750/400</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	750 / 850 400 / 500	58.8 / 61 ±2 56 / 58 ±2	20 / 20 20 / 20	4000	6 HU, 630 mm	70
<a href="#">BLWA 0810-750/500</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	750 / 850 500 / 600	58.8 / 61 ±2 57 / 59 ±2	20 / 20 20 / 20	4000	6 HU, 630 mm	70
<a href="#">BLWA 0810-1000/400</a>	80 ... 1000 MHz 80 ... 200 MHz 200 ... 1000 MHz	1000 / 1100 400 / 500	60 / 62 ±2 56 / 58 ±2	18 / 20 20 / 20	4000	6 HU, 630 mm	73
<a href="#">BLWA 0810-1000/500D</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	1000 / 1150 500 / 600	60 / 62 ±2 57 / 59 ±2	20 / 15 20 / 20	9000	21 HU, 800 mm	220
<a href="#">BLWA 0810-1000</a>	80 ... 1000 MHz	1000 / 1200	60 / 62 ±2	20 / 20	8500	15 HU, 800 mm	180
<a href="#">BLWA 0810-1400/700</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	1400 / 1500 700 / 850	61.5 / 64 ±2 58.4 / 61 ±2	20 / 20 20 / 20	10500	15 HU, 800 mm	190
<a href="#">BLWA 0810-1500/700D</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	1500 / 1700 700 / 850	61.8 / 64 ±2 58.4 / 61 ±2	20 / 15 20 / 20	11000	24 HU, 800 mm	300
<a href="#">BLWA 0810-1500/900</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	1500 / 1600 900 / 950	61.8 / 64 ±2 59.5 / 62 ±2	20 / 20 20 / 20	10500	18 HU, 800 mm	190
<a href="#">BLWA 0810-1500/1000D</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	1500 / 1700 1000 / 1150	61.8 / 64 ±2 60 / 62 ±2	20 / 15 20 / 20	11000	41 HU, 800 mm	400
<a href="#">BLWA 0810-1500/1200</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	1500 / 1700 1200 / 1300	61.8 / 64 ±2 60 / 62 ±2	20 / 20 20 / 20	17000	24 HU, 800 mm	315
<a href="#">BLWA 0810-1500D</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	1500 / 1700 1500 / 1700	61.8 / 64 ±2 61.8 / 64 ±2	20 / 15 20 / 20	11000	37 HU, 800 mm	450
<a href="#">BLWA 0810-1700/1350</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	1700 / 1850 1350 / 1500	62.3 / 65 ±2 61.3 / 64 ±2	20 / 20 20 / 20	20000	24 HU, 800 mm	300
<a href="#">BLWA 0810-2000/1000/700</a>	80 ... 1000 MHz 80 ... 280 MHz 280 ... 480 MHz 480 ... 1000 MHz	2000 / 2200 1000 / 1150 700 / 750	63 / 65 ±2 60 / 62 ±2 58.4 / 61 ±2	20 / 20 20 / 20 20 / 20	15000	24 HU, 800 mm	300
<a href="#">BLWA 0810-2000/1000D</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	2000 / 2200 1000 / 1150	63 / 65 ±2 60 / 62 ±2	20 / 15 20 / 20	18000	2x 32 HU, 800 mm	550
<a href="#">BLWA 0810-2000/1500D</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	2000 / 2200 1500 / 1700	63 / 65 ±2 61.8 / 64 ±2	20 / 15 20 / 20	18000	2x 32 HU, 800 mm	600
<a href="#">BLWA 0810-2000/1500</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	2000 / 2200 1500 / 1700	63 / 65 ±2 61.8 / 64 ±2	20 / 20 20 / 20	17000	24 HU, 800 mm	310
<a href="#">BLWA 0810-2000</a>	80 ... 1000 MHz	2000 / 2200	63 / 65 ±2	20 / 20	32000	32 HU, 800 mm	380
<a href="#">BLWA 0810-3000/2000D</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	3000 / 3500 2000 / 2200	64.8 / 67 ±2 63 / 65 ±2	20 / 20 20 / 20	25000	2x 32 HU, 800 mm	700
<a href="#">BLWA 0810-5000/3000D</a>	80 ... 1000 MHz 80 ... 400 MHz 400 ... 1000 MHz	5000 / 5500 3000 / 3500	67 / 69 ±2 65 / 67 ±2	20 / 20 20 / 20	45000	3x 37 HU, 800 mm	1200

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
-------	-----------------	---	-------------------------	-------------------------------	------------------	------------------------------------	--------------

<a href="#">BLWA 0820-150D</a>	80 ... 2000 MHz 80 ... 500 MHz 500 ... 2000 MHz	150 / 180 150 / 180	51.8 / 54 ±2 51.8 / 54 ±2	20 / 15 15 / 20	900	5 HU, 630 mm	38
--------------------------------	---	------------------------	------------------------------	--------------------	-----	--------------	----

<a href="#">BLWA 0820-200/100/30D</a>	80 ... 2000 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 2000 MHz	200 / 240 100 / 150 30 / 35	53 / 55 ±2 50 / 52 ±2 44.8 / 47 ±2	20 / 15 20 / 20 20 / 20	800	5 HU, 630 mm	36
---------------------------------------	--	-----------------------------------	--	-------------------------------	-----	--------------	----

<a href="#">BLWA 0820-200/100/60D</a>	80 ... 2000 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 2000 MHz	200 / 240 100 / 150 60 / 70	53 / 55 ±2 50 / 52 ±2 47.8 / 50 ±2	20 / 15 20 / 20 20 / 20	800	5 HU, 630 mm	38
---------------------------------------	--	-----------------------------------	--	-------------------------------	-----	--------------	----

<a href="#">BLWA 0820-200D</a>	80 ... 2000 MHz 80 ... 500 MHz 500 ... 2000 MHz	200 / 240 200 / 240	53 / 55 ±2 53 / 56 ±3	20 / 20 15 / 15	1100	4 HU, 630 mm	39
--------------------------------	---	------------------------	--------------------------	--------------------	------	--------------	----

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
-------	-----------------	---	-------------------------	-------------------------------	------------------	------------------------------------	--------------

<a href="#">BLWA 0825-200/100/35D</a>	80 ... 2500 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 2500 MHz	200 / 240 100 / 150 35 / 40	53 / 55 ±2 50 / 52 ±2 45.4 / 48 ±2	20 / 15 20 / 20 20 / 20	800	5 HU, 630 mm	38
---------------------------------------	--	-----------------------------------	--	-------------------------------	-----	--------------	----

<a href="#">BLWA 0825-200/100/70D</a>	80 ... 2500 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 2500 MHz	200 / 240 100 / 150 70 / 80	53 / 55 ±2 50 / 52 ±2 48.5 / 51 ±2	20 / 15 20 / 20 20 / 20	800	6 HU, 630 mm	54
---------------------------------------	--	-----------------------------------	--	-------------------------------	-----	--------------	----

<a href="#">BLWA 0825-200/150D</a>	80 ... 2500 MHz 80 ... 500 MHz 500 ... 2500 MHz	200 / 225 150 / 180	53 / 55 ±2 51.8 / 54 ±2	20 / 20 15 / 20	1150	4 HU, 630 mm	39
------------------------------------	---	------------------------	----------------------------	--------------------	------	--------------	----

Model	Frequency Range	Output Power P <sub>N</sub> min / typ	Gain min / typ	Harmonics 2nd / 3rd	Line Power	Dimensions (H, D)	Weight
-------	-----------------	--	-------------------	------------------------	------------	----------------------	--------

		W	dB	dBc	VA	19"-System	kg
<a href="#">BLWA 0830-10D</a>	80 ... 3000 MHz 80 ... 1000 MHz 1000 ... 3000 MHz	10 / 15 10 / 15	40 / 42 ±2 40 / 42 ±2	20 / 20 15 / 20	180	2 HU, 430 mm	14
<a href="#">BLWA 0830-30/20D</a>	80 ... 3000 MHz 80 ... 1000 MHz 1000 ... 3000 MHz	30 / 35 20 / 25	44.8 / 47 ±2 43 / 45 ±2	25 / 20 15 / 20	360	2 HU, 430 mm	14
<a href="#">BLWA 0830-30D</a>	80 ... 3000 MHz 80 ... 1000 MHz 1000 ... 3000 MHz	30 / 35 30 / 35	44.8 / 47 ±2 44.8 / 48 ±3	20 / 20 15 / 20	200	2 HU, 430 mm	14
<a href="#">BLWA 0830-50/40D</a>	80 ... 3000 MHz 80 ... 500 MHz 500 ... 3000 MHz	50 / 80 40 / 60	47 / 50 ±3 46 / 49 ±3	20 / 15 15 / 20	450	3 HU, 430 mm	17
<a href="#">BLWA 0830-50D</a>	80 ... 3000 MHz 80 ... 500 MHz 500 ... 3000 MHz	50 / 80 50 / 80	47 / 49 ±2 47 / 49 ±2	20 / 15 15 / 20	450	3 HU, 430 mm	17
<a href="#">BLWA 0830-200/100/20D</a>	80 ... 3000 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 3000 MHz	200 / 240 100 / 150 20 / 25	53 / 55 ±2 50 / 52 ±2 43 / 45 ±2	20 / 15 20 / 20 15 / 20	900	5 HU, 630 mm	35
<a href="#">BLWA 0830-200/100/40D</a>	80 ... 3000 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 3000 MHz	200 / 240 100 / 150 40 / 50	53 / 55 ±2 50 / 52 ±2 46 / 48 ±2	20 / 15 20 / 20 15 / 20	800	5 HU, 630 mm	36
<a href="#">BLWA 0830-200/100/80D</a>	80 ... 3000 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 3000 MHz	200 / 240 100 / 150 80 / 100	53 / 55 ±2 50 / 52 ±2 49 / 51 ±2	20 / 15 20 / 20 12 / 20	800	5 HU, 630 mm	38
<a href="#">BLWA 0830-200D</a>	80 ... 3000 MHz 80 ... 1000 MHz 1000 ... 3000 MHz	200 / 250 200 / 220	53 / 55 ±2 53 / 55 ±2	20 / 20 15 / 20	1800	8 HU, 630 mm	72
<a href="#">BLWA 0830-250/100D</a>	80 ... 3000 MHz 80 ... 500 MHz 500 ... 3000 MHz	250 / 300 100 / 120	54 / 56 ±2 50 / 52 ±2	25 / 20 15 / 20	1200	4 HU, 630 mm	38
<a href="#">BLWA 0830-250/200/40D</a>	80 ... 3000 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 3000 MHz	250 / 300 200 / 250 40 / 50	54 / 56 ±2 53 / 55 ±2 46 / 48 ±2	20 / 20 20 / 20 15 / 20	1900	6 HU, 630 mm	65
<a href="#">BLWA 0830-250/200/80D</a>	80 ... 3000 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 3000 MHz	250 / 300 200 / 250 80 / 100	54 / 56 ±2 53 / 55 ±2 49 / 51 ±2	20 / 20 20 / 20 12 / 20	1900	6 HU, 630 mm	67
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0840-200/100/60/30D</a>	80 ... 4000 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 2000 MHz 2000 ... 4000 MHz	200 / 240 100 / 150 60 / 70 30 / 35	55 / 57 ±2 50 / 52 ±2 47.8 / 50 ±2 44.8 / 47 ±2	20 / 15 20 / 20 20 / 20 20 / 20	800	6 HU, 630 mm	62
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0860-10D</a>	80 ... 6000 MHz 80 ... 1000 MHz 1000 ... 6000 MHz	10 / 12 10 / 12	40 / 42 ±2 40 / 42 ±2	20 / 20 15 / 20	270	2 HU, 430 mm	15
<a href="#">BLWA 0860-30D</a>	80 ... 6000 MHz 80 ... 1000 MHz 1000 ... 6000 MHz	30 / 35 30 / 35	44.8 / 47 ±2 44.8 / 47 ±2	20 / 20 15 / 20	500	2 HU, 430 mm	15
<a href="#">BLWA 0860-50/20D</a>	80 ... 6000 MHz 80 ... 1000 MHz 1000 ... 6000 MHz	50 / 60 20 / 30	47 / 49 ±2 43 / 46 ±3	20 / 20 15 / 20	700	3 HU, 430 mm	18
<a href="#">BLWA 0860-200/100/50D</a>	80 ... 6000 MHz 80 ... 400 MHz 400 ... 1000 MHz 1000 ... 6000 MHz	200 / 250 100 / 120 50 / 55	53 / 55 ±2 50 / 53 ±3 47 / 50 ±3	20 / 20 20 / 20 15 / 20	1900	4 HU, 630 mm	56
<a href="#">BLWA 0860-200/100D</a>	80 ... 6000 MHz 80 ... 1000 MHz 1000 ... 6000 MHz	200 / 250 100 / 120	53 / 55 ±2 50 / 53 ±3	20 / 20 15 / 20	1900	5 HU, 630 mm	58
<a href="#">BLWA 0860-250/100D</a>	80 ... 6000 MHz 80 ... 1000 MHz 1000 ... 6000 MHz	250 / 300 100 / 120	54 / 56 ±2 50 / 53 ±3	20 / 20 15 / 20	2050	6 HU, 630 mm	62
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 0818-10D</a>	80 ... 18000 MHz 80 ... 2000 MHz 2000 ... 6000 MHz 6000 ... 18000 MHz	10 / 12 10 / 12 10 / 12	40 / 43 ±3 40 / 43 ±3 40 / 43 ±3	12 / 15 15 / 15 15 / 20	200	3 HU, 430 mm	21
<a href="#">BLWA 0818-30/20D</a>	80 ... 18000 MHz 80 ... 1000 MHz 1000 ... 6000 MHz 6000 ... 18000 MHz	30 / 35 20 / 25 20 / 25	44.8 / 47 ±2 43 / 46 ±3 43 / 46 ±3	20 / 20 15 / 20 15 / 20	400	3 HU, 630 mm	27
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 1050-100</a>	100 ... 500 MHz	100 / 120	50 / 52 ±2	20 / 12	400	3 HU, 430 mm	19



<a href="#">BLWA 1050-150</a>	100 ... 500 MHz	150 / 180	51.8 / 54 ±2	20 / 15	800	3 HU, 430 mm	24
<a href="#">BLWA 1050-250</a>	100 ... 500 MHz	250 / 300	54 / 56 ±2	20 / 15	1500	3 HU, 630 mm	35
<a href="#">BLWA 1050-500</a>	100 ... 500 MHz	500 / 600	57 / 59 ±2	20 / 15	3000	6 HU, 630 mm	55
<a href="#">BLWA 1050-750</a>	100 ... 500 MHz	750 / 900	58.8 / 61 ±2	20 / 15	4500	8 HU, 630 mm	120
<a href="#">BLWA 1050-1000</a>	100 ... 500 MHz	1000 / 1150	60 / 62 ±2	20 / 15	8000	16 HU, 630 mm	180
<a href="#">BLWA 1050-1500</a>	100 ... 500 MHz	1500 / 1700	61.8 / 64 ±2	20 / 15	10000	21 HU, 800 mm	200
<a href="#">BLWA 1050-2000</a>	100 ... 500 MHz	2000 / 2200	63 / 65 ±2	20 / 15	17000	41 HU, 800 mm	300
<a href="#">BLWA 1050-2500</a>	100 ... 500 MHz	2500 / 2700	64 / 66 ±2	20 / 15	20000	41 HU, 800 mm	400
<a href="#">BLWA 1050-4000</a>	100 ... 500 MHz	4000 / 4400	66 / 68 ±2	20 / 15	35000	2x 32 HU, 800 mm	600
<a href="#">BLWA 1050-5000</a>	100 ... 500 MHz	5000 / 5500	67 / 69 ±2	20 / 15	45000	2x 32 HU, 800 mm	800

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 2050-100</a>	200 ... 500 MHz	100 / 120	50 / 52 ±2	20 / 15	400	3 HU, 430 mm	19
<a href="#">BLWA 2050-150</a>	200 ... 500 MHz	150 / 180	51.8 / 54 ±2	20 / 15	800	3 HU, 430 mm	24
<a href="#">BLWA 2050-300</a>	200 ... 500 MHz	300 / 330	54.8 / 57 ±2	20 / 20	1500	3 HU, 630 mm	35
<a href="#">BLWA 2050-500</a>	200 ... 500 MHz	500 / 600	57 / 59 ±2	20 / 20	2500	5 HU, 630 mm	43
<a href="#">BLWA 2050-750</a>	200 ... 500 MHz	750 / 850	58.8 / 61 ±2	20 / 20	4000	6 HU, 630 mm	80
<a href="#">BLWA 2050-1000</a>	200 ... 500 MHz	1000 / 1150	60 / 62 ±2	20 / 20	6000	8 HU, 630 mm	120
<a href="#">BLWA 2050-1500</a>	200 ... 500 MHz	1500 / 1700	61.8 / 64 ±2	20 / 20	8000	16 HU, 630 mm	180
<a href="#">BLWA 2050-2000</a>	200 ... 500 MHz	2000 / 2200	63 / 65 ±2	20 / 20	10000	19 HU, 630 mm	200
<a href="#">BLWA 2050-2500</a>	200 ... 500 MHz	2500 / 2700	64 / 66 ±2	20 / 20	17000	41 HU, 800 mm	300
<a href="#">BLWA 2050-3500</a>	200 ... 500 MHz	3500 / 4000	65.4 / 68 ±2	20 / 20	20000	41 HU, 800 mm	400
<a href="#">BLWA 2050-4500</a>	200 ... 500 MHz	4500 / 5000	65.5 / 68 ±2	20 / 20	35000	2x 32 HU, 800 mm	600
<a href="#">BLWA 2050-6000</a>	200 ... 500 MHz	6000 / 6500	67.8 / 70 ±2	20 / 20	45000	2x 32 HU, 800 mm	600

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 2010-10</a>	200 ... 1000 MHz	10 / 13	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	12
<a href="#">BLWA 2010-30</a>	200 ... 1000 MHz	30 / 40	44.8 / 47 ±2	20 / 20	200	2 HU, 430 mm	12
<a href="#">BLWA 2010-40</a>	200 ... 1000 MHz	40 / 45	46 / 48 ±2	20 / 20	300	2 HU, 430 mm	13
<a href="#">BLWA 2010-60</a>	200 ... 1000 MHz	60 / 70	47.8 / 50 ±2	20 / 20	400	3 HU, 430 mm	22
<a href="#">BLWA 2010-125</a>	200 ... 1000 MHz	125 / 140	51 / 53 ±2	20 / 20	800	3 HU, 630 mm	25
<a href="#">BLWA 2010-200/100</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	200 / 250 100 / 120	53 / 55 ±2 50 / 52 ±2	20 / 20 20 / 20	800	3 HU, 630 mm	24
<a href="#">BLWA 2010-250</a>	200 ... 1000 MHz	250 / 300	54 / 56 ±2	25 / 20	1900	4 HU, 630 mm	40
<a href="#">BLWA 2010-400</a>	200 ... 1000 MHz	400 / 450	56 / 58 ±2	20 / 20	3300	9 HU, 630 mm	92
<a href="#">BLWA 2010-500/350D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	500 / 600 350 / 400	57 / 59 ±2 55.4 / 58 ±2	20 / 20 20 / 20	3300	9 HU, 630 mm	95
<a href="#">BLWA 2010-750/350D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	750 / 900 350 / 400	58.8 / 61 ±2 55.5 / 58 ±2	20 / 20 20 / 20	5000	13 HU, 630 mm	135
<a href="#">BLWA 2010-750/500D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	750 / 900 500 / 600	58.8 / 61 ±2 57 / 59 ±2	20 / 20 20 / 20	5000	13 HU, 630 mm	135
<a href="#">BLWA 2010-750/700D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	750 / 900 700 / 850	58.8 / 61 ±2 58.5 / 61 ±2	20 / 20 20 / 20	5000	13 HU, 630 mm	135
<a href="#">BLWA 2010-750</a>	200 ... 1000 MHz	750 / 850	58.8 / 61 ±2	20 / 15	7000	15 HU, 800 mm	180
<a href="#">BLWA 2010-1000/500D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	1000 / 1150 500 / 600	60 / 62 ±2 58.5 / 61 ±2	20 / 20 20 / 20	6000	15 HU, 630 mm	140
<a href="#">BLWA 2010-1000/500</a>	200 ... 1000 MHz 200 ... 380 MHz 380 ... 500 MHz 500 ... 1000 MHz	1000 / 1150 700 / 750 500 / 550	60 / 62 ±2 58.4 / 61 ±2 57 / 59 ±2	20 / 15 20 / 20 20 / 20	4000	6 HU, 630 mm	69
<a href="#">BLWA 2010-1000/700D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	1000 / 1150 700 / 850	60 / 62 ±2 58.5 / 61 ±2	20 / 20 20 / 20	6000	15 HU, 630 mm	140
<a href="#">BLWA 2010-1200</a>	200 ... 1000 MHz	1200 / 1400	60.8 / 63 ±2	20 / 20	12500	24 HU, 800 mm	250
<a href="#">BLWA 2010-1500/700D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	1500 / 1700 700 / 850	61.8 / 64 ±2 58.5 / 61 ±2	20 / 20 20 / 20	10000	24 HU, 800 mm	280
<a href="#">BLWA 2010-1500/1000D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	1500 / 1700 1000 / 1150	61.8 / 64 ±2 60 / 62 ±2	20 / 20 20 / 20	10000	41 HU, 800 mm	350
<a href="#">BLWA 2010-1500D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	1500 / 1700 1500 / 1700	61.8 / 64 ±2 61.8 / 64 ±2	20 / 20 20 / 20	10000	37 HU, 800 mm	400
<a href="#">BLWA 2010-2000/1000</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	2000 / 2200 1000 / 1150	61.8 / 64 ±2 60 / 62 ±2	20 / 20 20 / 20	15000	24 HU, 800 mm	300
<a href="#">BLWA 2010-2000/1500</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	2000 / 2200 1500 / 1700	63 / 65 ±2 61.8 / 64 ±2	20 / 20 20 / 20	17000	24 HU, 800 mm	310
<a href="#">BLWA 2010-2000D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	2000 / 2200 2000 / 2200	63 / 65 ±2 63 / 65 ±2	20 / 20 20 / 20	11000	2x 32 HU, 800 mm	600
<a href="#">BLWA 2010-2000</a>	200 ... 1000 MHz	2000 / 2200	63 / 65 ±2	20 / 20	32000	2x 24 HU, 800 mm	610

<a href="#">BLWA 2010-3000/2000D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	3000 / 3500 2000 / 2200	65 / 67 ±2 63 / 65 ±2	20 / 20 20 / 20	25000	2x 32 HU, 800 mm	700
<a href="#">BLWA 2010-3000</a>	200 ... 1000 MHz	3000 / 3300	64.8 / 67 ±2	20 / 20	35000	2x 24 HU, 800 mm	680
<a href="#">BLWA 2010-5000D</a>	200 ... 1000 MHz 200 ... 500 MHz 500 ... 1000 MHz	5000 / 5500 5000 / 5500	67 / 69 ±2 67 / 69 ±2	20 / 20 20 / 20	45000	3x 37 HU, 800 mm	1000
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 4045-250</a>	400 ... 450 MHz	250 / 300	54 / 55 ±1	15 / 15	1000	4 HU, 630 mm	38
<a href="#">BLWA 4045-500</a>	400 ... 450 MHz	500 / 600	57 / 58 ±1	15 / 15	2000	5 HU, 630 mm	48
<a href="#">BLWA 4045-1000</a>	400 ... 450 MHz	1000 / 1100	60 / 61 ±1	15 / 15	4000	6 HU, 630 mm	62
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 4010-100</a>	400 ... 1000 MHz	100 / 120	50 / 52 ±2	20 / 25	500	3 HU, 630 mm	18
<a href="#">BLWA 4010-125</a>	400 ... 1000 MHz	125 / 140	51 / 53 ±2	20 / 20	580	3 HU, 630 mm	22
<a href="#">BLWA 4010-200</a>	400 ... 1000 MHz	200 / 230	53 / 55 ±2	20 / 20	1000	3 HU, 630 mm	30
<a href="#">BLWA 4010-250</a>	400 ... 1000 MHz	250 / 300	54 / 56 ±2	20 / 20	1200	4 HU, 630 mm	32
<a href="#">BLWA 4010-350</a>	400 ... 1000 MHz	350 / 400	55.4 / 58 ±2	20 / 20	2200	4 HU, 630 mm	32
<a href="#">BLWA 4010-500</a>	400 ... 1000 MHz	500 / 600	57 / 59 ±2	20 / 20	2700	5 HU, 630 mm	35
<a href="#">BLWA 4010-700</a>	400 ... 1000 MHz	700 / 750	58.5 / 61 ±2	20 / 20	4000	8 HU, 630 mm	82
<a href="#">BLWA 4010-1000</a>	400 ... 1000 MHz	1000 / 1150	60 / 62 ±2	20 / 20	4500	8 HU, 630 mm	85
<a href="#">BLWA 4010-1250</a>	400 ... 1000 MHz	1250 / 1300	61 / 63 ±2	20 / 20	6000	18 HU, 800 mm	150
<a href="#">BLWA 4010-1500</a>	400 ... 1000 MHz	1500 / 1700	61.8 / 64 ±2	20 / 20	7500	18 HU, 800 mm	150
<a href="#">BLWA 4010-2000</a>	400 ... 1000 MHz	2000 / 2200	63 / 65 ±2	20 / 20	12000	24 HU, 800 mm	250
<a href="#">BLWA 4010-3000</a>	400 ... 1000 MHz	3000 / 3300	64.8 / 67 ±2	20 / 20	15000	24 HU, 800 mm	250
<a href="#">BLWA 4010-4000</a>	400 ... 1000 MHz	4000 / 4500	66 / 68 ±2	20 / 20	28000	37 HU, 800 mm	450
<a href="#">BLWA 4010-5000</a>	400 ... 1000 MHz	5000 / 5500	67 / 69 ±2	20 / 20	34000	37 HU, 800 mm	450
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 5010-100</a>	500 ... 1000 MHz	100 / 120	50 / 52 ±2	20 / 20	500	3 HU, 630 mm	18
<a href="#">BLWA 5010-125</a>	500 ... 1000 MHz	125 / 140	51 / 53 ±2	20 / 20	500	3 HU, 630 mm	20
<a href="#">BLWA 5010-200</a>	500 ... 1000 MHz	200 / 230	53 / 55 ±2	20 / 20	1000	3 HU, 630 mm	30
<a href="#">BLWA 5010-250</a>	500 ... 1000 MHz	250 / 300	54 / 56 ±2	20 / 20	1200	3 HU, 630 mm	32
<a href="#">BLWA 5010-350</a>	500 ... 1000 MHz	350 / 400	55.4 / 58 ±2	20 / 20	2200	4 HU, 630 mm	32
<a href="#">BLWA 5010-500</a>	500 ... 1000 MHz	500 / 600	57 / 59 ±2	20 / 20	2700	5 HU, 630 mm	35
<a href="#">BLWA 5010-700</a>	500 ... 1000 MHz	700 / 750	58.5 / 61 ±2	20 / 20	4000	8 HU, 630 mm	82
<a href="#">BLWA 5010-1000</a>	500 ... 1000 MHz	1000 / 1150	60 / 62 ±2	20 / 20	4500	8 HU, 630 mm	85
<a href="#">BLWA 5010-1250</a>	500 ... 1000 MHz	1250 / 1300	61 / 63 ±2	20 / 20	6000	18 HU, 800 mm	150
<a href="#">BLWA 5010-1500</a>	500 ... 1000 MHz	1500 / 1700	61.8 / 64 ±2	20 / 20	7500	18 HU, 800 mm	150
<a href="#">BLWA 5010-2000</a>	500 ... 1000 MHz	2000 / 2200	63 / 65 ±2	20 / 20	12000	24 HU, 800 mm	250
<a href="#">BLWA 5010-3000</a>	500 ... 1000 MHz	3000 / 3300	64.8 / 67 ±2	20 / 20	15000	24 HU, 800 mm	250
<a href="#">BLWA 5010-4000</a>	500 ... 1000 MHz	4000 / 4500	66 / 68 ±2	20 / 20	28000	37 HU, 800 mm	450
<a href="#">BLWA 5010-5000</a>	500 ... 1000 MHz	5000 / 5500	67 / 69 ±2	20 / 20	34000	37 HU, 800 mm	450
Cellular Bands							
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 8010-10</a>	800 ... 1000 MHz	10 / 13	40 / 42 ±2	25 / 25	75	2 HU, 430 mm	12
<a href="#">BLWA 8010-25</a>	800 ... 1000 MHz	25 / 30	44 / 46 ±2	25 / 25	150	2 HU, 430 mm	12
<a href="#">BLWA 8010-50</a>	800 ... 1000 MHz	50 / 60	47 / 49 ±2	50 / 50	300	3 HU, 430 mm	15
<a href="#">BLWA 8010-90</a>	800 ... 1000 MHz	90 / 110	49.5 / 52 ±2	50 / 50	500	3 HU, 430 mm	18
<a href="#">BLWA 8010-175</a>	800 ... 1000 MHz	175 / 190	52.4 / 55 ±2	50 / 50	1200	4 HU, 630 mm	35
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 8996-10</a>	890 ... 960 MHz	10 / 13	40 / 42 ±2	25 / 25	75	2 HU, 430 mm	12
<a href="#">BLWA 8996-25</a>	890 ... 960 MHz	25 / 30	44 / 46 ±2	25 / 25	150	2 HU, 430 mm	12
<a href="#">BLWA 8996-50</a>	890 ... 960 MHz	50 / 60	47 / 49 ±2	50 / 50	300	3 HU, 430 mm	15
<a href="#">BLWA 8996-100</a>	890 ... 960 MHz	100 / 115	50 / 52 ±2	50 / 50	500	3 HU, 430 mm	18
<a href="#">BLWA 8996-200</a>	890 ... 960 MHz	200 / 220	53 / 55 ±2	50 / 50	1200	4 HU, 630 mm	35
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLWA 9396-10</a>	930 ... 960 MHz	10 / 13	40 / 42 ±2	25 / 25	75	2 HU, 430 mm	11
<a href="#">BLWA 9396-25</a>	930 ... 960 MHz	25 / 30	44 / 46 ±2	25 / 25	150	2 HU, 430 mm	12
<a href="#">BLWA 9396-50</a>	930 ... 960 MHz	50 / 60	47 / 49 ±2	50 / 50	300	3 HU, 430 mm	15
<a href="#">BLWA 9396-100</a>	930 ... 960 MHz	100 / 115	50 / 52 ±2	50 / 50	500	3 HU, 430 mm	18
<a href="#">BLWA 9396-200</a>	930 ... 960 MHz	200 / 220	53 / 55 ±2	50 / 50	1200	4 HU, 630 mm	35
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1719-10</a>	1.7 ... 1.9 GHz	10 / 13	40 / 42 ±2	50 / 50	75	2 HU, 430 mm	12
<a href="#">BLMA 1719-20</a>	1.7 ... 1.9 GHz	20 / 25	43 / 45 ±2	50 / 50	180	2 HU, 430 mm	13

Anzahl Modellreihen: 11

<a href="#">BLMA 1719-40</a>	1.7 ... 1.9 GHz	40 / 50	46 / 48 ±2	50 / 50	500	3 HU, 430 mm	20
<a href="#">BLMA 1719-80</a>	1.7 ... 1.9 GHz	80 / 100	49 / 51 ±2	50 / 50	650	3 HU, 430 mm	25
<a href="#">BLMA 1719-200</a>	1.7 ... 1.9 GHz	200 / 220	53 / 55 ±2	50 / 50	1500	4 HU, 630 mm	40
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1820-120</a>	1.8 ... 2 GHz	120 / 140	51 / 53 ±2	50 / 50	750	4 HU, 630 mm	27
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1822-10</a>	1.8 ... 2.2 GHz	10 / 13	40 / 42 ±2	50 / 50	75	2 HU, 430 mm	12
<a href="#">BLMA 1822-20</a>	1.8 ... 2.2 GHz	20 / 25	43 / 45 ±2	50 / 50	200	2 HU, 430 mm	14
<a href="#">BLMA 1822-40</a>	1.8 ... 2.2 GHz	40 / 50	46 / 48 ±2	50 / 50	350	3 HU, 430 mm	16
<a href="#">BLMA 1822-100</a>	1.8 ... 2.2 GHz	100 / 110	50 / 52 ±2	50 / 50	750	3 HU, 630 mm	27
<a href="#">BLMA 1822-180</a>	1.8 ... 2.2 GHz	180 / 200	52 / 54 ±2	50 / 50	1500	4 HU, 630 mm	40
<a href="#">BLMA 1822-200/150</a>	1.8 ... 2.2 GHz 1.8 ... 2.2 GHz 1.9 ... 2.1 GHz	150 / 170 200 / 220	51.8 / 54 ±2 53 / 55 ±2	50 / 50 50 / 50	1500	4 HU, 630 mm	40
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1921-10</a>	1.9 ... 2.1 GHz	10 / 13	40 / 42 ±2	50 / 50	75	2 HU, 430 mm	12
<a href="#">BLMA 1921-25</a>	1.9 ... 2.1 GHz	25 / 30	44 / 46 ±2	50 / 50	200	2 HU, 430 mm	14
<a href="#">BLMA 1921-50</a>	1.9 ... 2.1 GHz	50 / 60	47 / 49 ±2	50 / 50	350	2 HU, 430 mm	16
<a href="#">BLMA 1921-100</a>	1.9 ... 2.1 GHz	100 / 110	50 / 52 ±2	50 / 50	650	3 HU, 630 mm	25
<a href="#">BLMA 1921-200</a>	1.9 ... 2.1 GHz	200 / 210	53 / 55 ±2	50 / 50	1500	4 HU, 630 mm	40
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2021-50</a>	2110 ... 2170 MHz	50 / 60	47 / 49 ±2	50 / 50	400	3 HU, 430 mm	25
<a href="#">BLMA 2021-100</a>	2110 ... 2170 MHz	100 / 110	50 / 52 ±2	50 / 50	750	3 HU, 630 mm	28
<a href="#">BLMA 2021-200</a>	2110 ... 2170 MHz	200 / 220	53 / 55 ±2	50 / 50	1800	4 HU, 630 mm	32
<a href="#">BLMA 2021-400</a>	2110 ... 2170 MHz	400 / 450	56 / 58 ±2	50 / 50	3600	7 HU, 630 mm	65
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2123-500</a>	2.1 ... 2.3 GHz	500 / 550	57 / 59 ±2	30 / 30	2450	4 HU, 630 mm	40
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2325-10</a>	2.3 ... 2.5 GHz	10 / 13	40 / 42 ±2	50 / 50	80	2 HU, 430 mm	12
<a href="#">BLMA 2325-25</a>	2.3 ... 2.5 GHz	25 / 30	44 / 46 ±2	50 / 50	180	2 HU, 430 mm	18
<a href="#">BLMA 2325-50</a>	2.3 ... 2.5 GHz	50 / 60	47 / 49 ±2	50 / 50	400	3 HU, 430 mm	25
<a href="#">BLMA 2325-100</a>	2.3 ... 2.5 GHz	100 / 110	50 / 52 ±2	50 / 50	800	3 HU, 630 mm	28
<a href="#">BLMA 2325-150</a>	2.3 ... 2.5 GHz	150 / 165	51.8 / 54 ±2	50 / 50	1500	4 HU, 630 mm	45
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2527-300</a>	2.5 ... 2.7 GHz	300 / 350	54.8 / 57 ±2	40 / 40	1500	4 HU, 630 mm	35
<a href="#">BLMA 2527-600</a>	2.5 ... 2.7 GHz	600 / 650	57.8 / 60 ±2	40 / 40	3000	5 HU, 630 mm	52

**BLMA**

Anzahl Modellreihen: 59

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0220-1</a>	0.2 ... 20 GHz	1 / 1.2	30 / 33 ±3	15 / 20	60	2 HU, 430 mm	9
<a href="#">BLMA 0220-2</a>	0.2 ... 20 GHz	2 / 2.2	33 / 36 ±3	15 / 20	70	2 HU, 430 mm	9
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0118-0.1</a>	0.1 ... 18 GHz	0.1 / 0.15	20 / 22 ±2	15 / 20	50	2 HU, 430 mm	11
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0120-1</a>	0.1 ... 20 GHz	1 / 1.2	30 / 33 ±3	15 / 20	60	2 HU, 430 mm	9
<a href="#">BLMA 0120-2</a>	0.1 ... 20 GHz	2 / 2.2	33 / 36 ±3	15 / 20	70	2 HU, 430 mm	9
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0126-0.1</a>	0.1 ... 26.5 GHz	0.1 / 0.15	20 / 23 ±3	15 / 20	30	2 HU, 430 mm	9
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0438-40</a>	0.4 ... 3.8 GHz	40 / 50	46 / 49 ±3	12 / 18	350	2 HU, 430 mm	13
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0460-5</a>	0.4 ... 6 GHz	5 / 10	37 / 40 ±3	12 / 20	180	2 HU, 430 mm	10

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0520-1</a>	0.5 ... 2 GHz	1 / 1.3	30 / 32 ±2	20 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 0520-2</a>	0.5 ... 2 GHz	2 / 2.2	33 / 35 ±2	20 / 20	100	2 HU, 430 mm	13
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0525-10</a>	0.5 ... 2.5 GHz	10 / 12	40 / 42 ±2	12 / 15	100	2 HU, 430 mm	11
<a href="#">BLMA 0525-20</a>	0.5 ... 2.5 GHz	20 / 30	43 / 45 ±2	12 / 15	150	2 HU, 430 mm	12
<a href="#">BLMA 0525-35</a>	0.5 ... 2.5 GHz	35 / 50	45.4 / 48 ±2	15 / 20	300	2 HU, 430 mm	13
<a href="#">BLMA 0525-75</a>	0.5 ... 2.5 GHz	75 / 100	48.8 / 51 ±2	12 / 20	500	3 HU, 430 mm	19
<a href="#">BLMA 0525-140</a>	0.5 ... 2.5 GHz	140 / 180	51.5 / 55 ±3	15 / 20	1000	3 HU, 630 mm	26
<a href="#">BLMA 0525-150S</a>	0.5 ... 2.5 GHz	150 / 180	51.5 / 54 ±2	15 / 20	1000	3 HU, 630 mm	26
<a href="#">BLMA 0525-200</a>	0.5 ... 2.5 GHz	200 / 220	53 / 56 ±3	15 / 20	1500	4 HU, 630 mm	36
<a href="#">BLMA 0525-250</a>	0.5 ... 2.5 GHz	250 / 300	54 / 56 ±2	15 / 20	2000	4 HU, 630 mm	39
<a href="#">BLMA 0525-400</a>	0.5 ... 2.5 GHz	400 / 450	56 / 59 ±3	15 / 20	3000	6 HU, 630 mm	62
<a href="#">BLMA 0525-500</a>	0.5 ... 2.5 GHz	500 / 600	57 / 59 ±2	15 / 20	3500	8 HU, 630 mm	88
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0530-10</a>	0.5 ... 3 GHz	10 / 15	40 / 42 ±2	15 / 20	150	2 HU, 430 mm	13
<a href="#">BLMA 0530-40</a>	0.5 ... 3 GHz	40 / 50	46 / 48 ±2	15 / 20	250	2 HU, 430 mm	13
<a href="#">BLMA 0530-50</a>	0.5 ... 3 GHz	50 / 70	47 / 49 ±2	15 / 20	400	2 HU, 430 mm	13
<a href="#">BLMA 0530-80</a>	0.5 ... 3 GHz	80 / 100	49 / 51 ±2	15 / 20	600	3 HU, 430 mm	16
<a href="#">BLMA 0530-150</a>	0.5 ... 3 GHz	150 / 200	51.8 / 54 ±2	15 / 20	1200	3 HU, 630 mm	29
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0560-10</a>	0.5 ... 6 GHz	10 / 12	40 / 43 ±3	12 / 20	200	2 HU, 430 mm	10
<a href="#">BLMA 0560-30D</a>	0.5 ... 6 GHz 0.5 ... 2.5 GHz 2.5 ... 6 GHz	30 / 35 30 / 35	44.8 / 47 ±2 44.8 / 47 ±2	15 / 20 20 / 20	400	3 HU, 430 mm	15
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0740-20</a>	0.7 ... 4 GHz	20 / 25	43 / 45 ±2	15 / 20	300	2 HU, 430 mm	14
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0760-1</a>	0.7 ... 6 GHz	1 / 1.2	30 / 32 ±3	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 0760-3</a>	0.7 ... 6 GHz	3 / 3.3	34.8 / 37 ±3	20 / 20	90	2 HU, 430 mm	11
<a href="#">BLMA 0760-6</a>	0.7 ... 6 GHz	6 / 10	37.8 / 40 ±3	15 / 20	180	2 HU, 430 mm	11
<a href="#">BLMA 0760-15</a>	0.7 ... 6 GHz	15 / 20	41.8 / 45 ±3	15 / 20	250	2 HU, 430 mm	12
<a href="#">BLMA 0760-25</a>	0.7 ... 6 GHz	25 / 30	44 / 47 ±3	15 / 20	450	2 HU, 430 mm	13
<a href="#">BLMA 0760-120</a>	0.7 ... 6 GHz	120 / 140	50.8 / 54 ±3	15 / 20	2100	4 HU, 630 mm	40
<a href="#">BLMA 0760-200</a>	0.7 ... 6 GHz	200 / 220	53 / 56 ±3	15 / 20	3200	5 HU, 630 mm	60
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0712-10D</a>	0.7 ... 12 GHz 0.7 ... 6.1 GHz 6.1 ... 12 GHz	10 / 12 10 / 12	40 / 43 ±3 40 / 43 ±3	15 / 20 12 / 20	320	3 HU, 430 mm	19
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0820-1</a>	0.8 ... 2 GHz	1 / 1.3	30 / 32 ±2	20 / 20	75	2 HU, 430 mm	10
<a href="#">BLMA 0820-3</a>	0.8 ... 2 GHz	3 / 3.5	34.8 / 37 ±2	20 / 20	75	2 HU, 430 mm	10
<a href="#">BLMA 0820-7</a>	0.8 ... 2 GHz	7 / 8	38.5 / 41 ±2	20 / 20	75	2 HU, 430 mm	10
<a href="#">BLMA 0820-10</a>	0.8 ... 2 GHz	10 / 12	40 / 42 ±2	15 / 20	150	2 HU, 430 mm	10
<a href="#">BLMA 0820-30</a>	0.8 ... 2 GHz	30 / 35	44.8 / 47 ±2	20 / 20	200	2 HU, 430 mm	13
<a href="#">BLMA 0820-50</a>	0.8 ... 2 GHz	50 / 60	47 / 49 ±2	20 / 20	350	3 HU, 550 mm	22
<a href="#">BLMA 0820-100</a>	0.8 ... 2 GHz	100 / 120	50 / 52 ±2	20 / 20	700	3 HU, 630 mm	22
<a href="#">BLMA 0820-200</a>	0.8 ... 2 GHz	200 / 240	53 / 55 ±2	20 / 20	1200	3 HU, 630 mm	26
<a href="#">BLMA 0820-400</a>	0.8 ... 2 GHz	400 / 450	56 / 58 ±2	20 / 20	2600	6 HU, 630 mm	50
<a href="#">BLMA 0820-750</a>	0.8 ... 2 GHz	750 / 900	58.8 / 61 ±2	20 / 20	6000	15 HU, 630 mm	150
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0822-1</a>	0.8 ... 2.2 GHz	1 / 1.3	30 / 32 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 0822-3</a>	0.8 ... 2.2 GHz	3 / 3.5	34.8 / 37 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 0822-7</a>	0.8 ... 2.2 GHz	7 / 8	38.5 / 41 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 0822-10</a>	0.8 ... 2.2 GHz	10 / 12	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	11
<a href="#">BLMA 0822-30</a>	0.8 ... 2.2 GHz	30 / 35	44.8 / 47 ±2	15 / 20	220	2 HU, 430 mm	12
<a href="#">BLMA 0822-50</a>	0.8 ... 2.2 GHz	50 / 60	47 / 49 ±2	20 / 20	350	3 HU, 430 mm	18
<a href="#">BLMA 0822-100</a>	0.8 ... 2.2 GHz	100 / 120	50 / 52 ±2	20 / 20	700	3 HU, 630 mm	22
<a href="#">BLMA 0822-200</a>	0.8 ... 2.2 GHz	200 / 240	53 / 55 ±2	20 / 20	1200	3 HU, 630 mm	26
<a href="#">BLMA 0822-400</a>	0.8 ... 2.2 GHz	400 / 450	56 / 58 ±2	20 / 20	2600	6 HU, 630 mm	50

<a href="#">BLMA 0822-750</a>	0.8 ... 2.2 GHz	750 / 900	58.8 / 61 ±2	20 / 20	6000	15 HU, 630 mm	150
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0825-1</a>	0.8 ... 2.5 GHz	1 / 1.3	30 / 32 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 0825-3</a>	0.8 ... 2.5 GHz	3 / 3.5	34.8 / 37 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 0825-5</a>	0.8 ... 2.5 GHz	5 / 6	37 / 39 ±2	20 / 20	75	2 HU, 430 mm	12
<a href="#">BLMA 0825-10</a>	0.8 ... 2.5 GHz	10 / 13	40 / 42 ±2	12 / 20	150	2 HU, 430 mm	13
<a href="#">BLMA 0825-20</a>	0.8 ... 2.5 GHz	20 / 25	43 / 45 ±2	20 / 20	250	2 HU, 430 mm	13
<a href="#">BLMA 0825-40</a>	0.8 ... 2.5 GHz	40 / 50	46 / 48 ±2	20 / 20	350	3 HU, 630 mm	18
<a href="#">BLMA 0825-75</a>	0.8 ... 2.5 GHz	75 / 90	58.8 / 51 ±2	20 / 20	800	3 HU, 630 mm	22
<a href="#">BLMA 0825-150</a>	0.8 ... 2.5 GHz	150 / 180	51.8 / 54 ±2	20 / 20	1200	3 HU, 630 mm	26
<a href="#">BLMA 0825-150S</a>	0.8 ... 2.5 GHz	150 / 180	51.8 / 54 ±2	18 / 20	1100	3 HU, 630 mm	25
<a href="#">BLMA 0825-200</a>	0.8 ... 2.5 GHz	200 / 220	53 / 55 ±2	20 / 20	1600	4 HU, 630 mm	35
<a href="#">BLMA 0825-250</a>	0.8 ... 2.5 GHz	250 / 300	54 / 56 ±2	12 / 15	2000	4 HU, 630 mm	36
<a href="#">BLMA 0825-300</a>	0.8 ... 2.5 GHz	300 / 350	54.8 / 57 ±2	20 / 20	2400	6 HU, 630 mm	52
<a href="#">BLMA 0825-300S</a>	0.8 ... 2.5 GHz	300 / 350	54.8 / 57 ±2	15 / 20	2000	4 HU, 630 mm	36
<a href="#">BLMA 0825-500S</a>	0.8 ... 2.5 GHz	500 / 650	57 / 59 ±2	18 / 20	3500	9 HU, 630 mm	86
<a href="#">BLMA 0825-500</a>	0.8 ... 2.5 GHz	500 / 550	57 / 59 ±2	20 / 20	5000	12 HU, 800 mm	105
<a href="#">BLMA 0825-750</a>	0.8 ... 2.5 GHz	750 / 850	58.8 / 61 ±2	18 / 20	4500	9 HU, 630 mm	105
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0827-1</a>	0.8 ... 2.7 GHz	1 / 1.3	30 / 32 ±2	20 / 20	70	2 HU, 430 mm	11
<a href="#">BLMA 0827-3</a>	0.8 ... 2.7 GHz	3 / 3.5	34.8 / 37 ±2	20 / 20	70	2 HU, 430 mm	11
<a href="#">BLMA 0827-5</a>	0.8 ... 2.7 GHz	5 / 6	37 / 39 ±2	20 / 20	70	2 HU, 430 mm	12
<a href="#">BLMA 0827-15</a>	0.8 ... 2.7 GHz	15 / 18	41.7 / 44 ±2	20 / 20	200	2 HU, 430 mm	11
<a href="#">BLMA 0827-30</a>	0.8 ... 2.7 GHz	30 / 35	43.8 / 46 ±2	20 / 20	350	3 HU, 630 mm	18
<a href="#">BLMA 0827-55</a>	0.8 ... 2.7 GHz	55 / 70	47.4 / 50 ±2	20 / 20	800	3 HU, 630 mm	22
<a href="#">BLMA 0827-110</a>	0.8 ... 2.7 GHz	110 / 140	50.4 / 53 ±2	20 / 20	1200	3 HU, 630 mm	26
<a href="#">BLMA 0827-220</a>	0.8 ... 2.7 GHz	220 / 250	53.4 / 56 ±2	20 / 20	1600	4 HU, 630 mm	35
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0830-1</a>	0.8 ... 3 GHz	1 / 1.3	30 / 32 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 0830-3</a>	0.8 ... 3 GHz	3 / 3.5	34.8 / 37 ±2	20 / 20	75	2 HU, 430 mm	12
<a href="#">BLMA 0830-6</a>	0.8 ... 3 GHz	6 / 7	37.8 / 40 ±2	20 / 20	100	2 HU, 430 mm	12
<a href="#">BLMA 0830-10</a>	0.8 ... 3 GHz	10 / 13	40 / 43 ±3	15 / 20	180	2 HU, 430 mm	13
<a href="#">BLMA 0830-20</a>	0.8 ... 3 GHz	20 / 25	43 / 45 ±2	15 / 20	250	2 HU, 430 mm	13
<a href="#">BLMA 0830-40</a>	0.8 ... 3 GHz	40 / 50	46 / 48 ±2	12 / 20	250	3 HU, 430 mm	18
<a href="#">BLMA 0830-80</a>	0.8 ... 3 GHz	80 / 100	49 / 51 ±2	15 / 20	450	3 HU, 430 mm	18
<a href="#">BLMA 0830-100</a>	0.8 ... 3 GHz	100 / 120	50 / 52 ±2	15 / 20	500	3 HU, 430 mm	18
<a href="#">BLMA 0830-150</a>	0.8 ... 3 GHz	150 / 180	51.8 / 54 ±2	15 / 20	1200	3 HU, 630 mm	30
<a href="#">BLMA 0830-200</a>	0.8 ... 3 GHz	200 / 230	53 / 55 ±2	15 / 20	1600	5 HU, 630 mm	42
<a href="#">BLMA 0830-250</a>	0.8 ... 3 GHz	250 / 300	54 / 56 ±2	15 / 20	2100	5 HU, 630 mm	51
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0840-30/20D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	30 / 35 20 / 35	44.8 / 47 ±2 43 / 45 ±2	20 / 20 20 / 20	200	3 HU, 430 mm	13
<a href="#">BLMA 0840-30/20</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	30 / 35 20 / 35	44.8 / 47 ±2 43 / 45 ±2	15 / 20 15 / 20	250	3 HU, 430 mm	15
<a href="#">BLMA 0840-30D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	30 / 35 30 / 35	44.8 / 47 ±2 44.8 / 47 ±2	20 / 20 20 / 20	350	3 HU, 630 mm	23
<a href="#">BLMA 0840-50/35D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	50 / 60 35 / 40	47 / 49 ±2 45.4 / 47 ±2	20 / 20 20 / 20	500	3 HU, 630 mm	23
<a href="#">BLMA 0840-50/60D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	50 / 60 60 / 75	47 / 49 ±2 47.8 / 50 ±2	20 / 20 20 / 20	600	3 HU, 630 mm	26
<a href="#">BLMA 0840-100/60D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	100 / 120 60 / 75	50 / 52 ±2 47.8 / 50 ±2	20 / 20 20 / 20	750	3 HU, 630 mm	28
<a href="#">BLMA 0840-100D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	100 / 120 100 / 120	50 / 52 ±2 50 / 52 ±2	20 / 20 20 / 20	1300	6 HU, 630 mm	42
<a href="#">BLMA 0840-200/100D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	200 / 240 100 / 120	53 / 55 ±2 50 / 52 ±2	20 / 20 20 / 20	1300	6 HU, 630 mm	45
<a href="#">BLMA 0840-200D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	200 / 240 200 / 240	53 / 55 ±2 53 / 55 ±2	20 / 20 20 / 20	2500	9 HU, 630 mm	72
<a href="#">BLMA 0840-200</a>	0.8 ... 4 GHz	200 / 250	53 / 55 ±2	18 / 20	2100	5 HU, 630 mm	53
<a href="#">BLMA 0840-270D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	270 / 300 270 / 300	54.3 / 57 ±2 54.3 / 57 ±2	20 / 20 20 / 20	2700	9 HU, 630 mm	78
<a href="#">BLMA 0840-350</a>	0.8 ... 4 GHz	350 / 400	55.4 / 59 ±3	20 / 20	6500	8 HU, 630 mm	92



<a href="#">BLMA 0840-400/200D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	400 / 450 200 / 240	56 / 58 ±2 53 / 55 ±2	20 / 20 20 / 20	3000	13 HU, 630 mm	105
<a href="#">BLMA 0840-400</a>	0.8 ... 4 GHz	400 / 450	56 / 59 ±3	20 / 20	6300	7 HU, 630 mm	85
<a href="#">BLMA 0840-750/400D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	750 / 900 400 / 450	58.8 / 61 ±2 56 / 58 ±2	20 / 20 20 / 20	8000	41 HU, 800 mm	230
<a href="#">BLMA 0840-1000D</a>	0.8 ... 4 GHz 0.8 ... 2 GHz 2 ... 4 GHz	1000 / 1200 1000 / 1200	60 / 62 ±2 60 / 62 ±2	20 / 20 20 / 20	8500	2x 24 HU, 800 mm	460
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0842-1</a>	0.8 ... 4.2 GHz	1 / 1.3	30 / 32 ±2	20 / 20	75	2 HU, 430 mm	10
<a href="#">BLMA 0842-3</a>	0.8 ... 4.2 GHz	3 / 3.5	34.8 / 37 ±2	20 / 20	80	2 HU, 430 mm	10
<a href="#">BLMA 0842-5</a>	0.8 ... 4.2 GHz	5 / 6	37 / 39 ±2	15 / 20	100	2 HU, 430 mm	10
<a href="#">BLMA 0842-10</a>	0.8 ... 4.2 GHz	10 / 13	40 / 42 ±2	15 / 20	300	2 HU, 430 mm	13
<a href="#">BLMA 0842-20</a>	0.8 ... 4.2 GHz	20 / 25	43 / 45 ±2	15 / 20	300	2 HU, 430 mm	14
<a href="#">BLMA 0842-60</a>	0.8 ... 4.2 GHz	60 / 80	47.8 / 50 ±2	18 / 20	600	3 HU, 630 mm	28
<a href="#">BLMA 0842-120</a>	0.8 ... 4.2 GHz	120 / 150	50.8 / 53 ±2	18 / 20	1200	3 HU, 630 mm	32
<a href="#">BLMA 0842-200</a>	0.8 ... 4.2 GHz	200 / 250	53 / 55 ±2	18 / 20	2500	5 HU, 630 mm	44
<a href="#">BLMA 0842-350</a>	0.8 ... 4.2 GHz	350 / 450	55.4 / 58 ±2	18 / 20	4500	8 HU, 630 mm	97
<a href="#">BLMA 0842-400</a>	0.8 ... 4.2 GHz	400 / 500	56 / 58 ±2	18 / 20	4500	8 HU, 630 mm	97
<a href="#">BLMA 0842-500</a>	0.8 ... 4.2 GHz	500 / 600	57 / 60 ±3	18 / 20	6000	10 HU, 630 mm	128
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0860-100D</a>	0.8 ... 6 GHz 0.8 ... 2 GHz 2 ... 6 GHz	100 / 125 100 / 125	50 / 52 ±2 50 / 52 ±2	20 / 20 20 / 20	1300	7 HU, 630 mm	65
<a href="#">BLMA 0860-30</a>	0.8 ... 6 GHz	30 / 35	44 / 46 ±2	15 / 20	500	2 HU, 430 mm	13
<a href="#">BLMA 0860-500</a>	0.8 ... 6 GHz	500 / 550	57 / 60 ±3	15 / 20	7000	12 HU, 800 mm	142
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0880-0.8</a>	0.8 ... 8 GHz	0.8 / 1	29 / 32 ±3	15 / 18	75	2 HU, 430 mm	11
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 0818-10D</a>	0.8 ... 18 GHz 0.8 ... 6 GHz 6 ... 18 GHz	10 / 12 10 / 12	40 / 43 ±3 40 / 43 ±3	15 / 20 12 / 20	200	3 HU, 430 mm	22
<a href="#">BLMA 0818-20D</a>	0.8 ... 18 GHz 0.8 ... 6 GHz 6 ... 18 GHz	20 / 25 20 / 22	43 / 46 ±3 43 / 46 ±3	15 / 20 15 / 20	370	3 HU, 430 mm	20
<a href="#">BLMA 0818-30/20D</a>	0.8 ... 18 GHz 0.8 ... 6 GHz 6 ... 18 GHz	30 / 35 20 / 22	44.8 / 48 ±3 43 / 46 ±3	15 / 20 15 / 20	430	3 HU, 430 mm	21
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1020-1</a>	1 ... 2 GHz	1 / 1.3	30 / 32 ±2	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 1020-3</a>	1 ... 2 GHz	3 / 3.5	34.8 / 37 ±2	20 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 1020-5</a>	1 ... 2 GHz	5 / 6	37 / 39 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 1020-10</a>	1 ... 2 GHz	10 / 13	40 / 42 ±2	18 / 20	100	2 HU, 430 mm	12
<a href="#">BLMA 1020-30</a>	1 ... 2 GHz	30 / 35	44.8 / 47 ±2	20 / 20	180	2 HU, 430 mm	12
<a href="#">BLMA 1020-50</a>	1 ... 2 GHz	50 / 60	47 / 49 ±2	15 / 20	500	2 HU, 430 mm	13
<a href="#">BLMA 1020-60</a>	1 ... 2 GHz	60 / 70	47.8 / 49 ±2	20 / 20	350	3 HU, 630 mm	21
<a href="#">BLMA 1020-100</a>	1 ... 2 GHz	100 / 125	50 / 52 ±2	20 / 20	600	3 HU, 630 mm	22
<a href="#">BLMA 1020-120</a>	1 ... 2 GHz	120 / 140	50.8 / 53 ±2	20 / 20	700	3 HU, 630 mm	22
<a href="#">BLMA 1020-200</a>	1 ... 2 GHz	200 / 240	53 / 55 ±2	20 / 20	1200	3 HU, 630 mm	27
<a href="#">BLMA 1020-240</a>	1 ... 2 GHz	240 / 270	53.8 / 55 ±2	20 / 20	1500	3 HU, 630 mm	27
<a href="#">BLMA 1020-300</a>	1 ... 2 GHz	300 / 330	57.8 / 60 ±2	15 / 20	2200	4 HU, 630 mm	39
<a href="#">BLMA 1020-400</a>	1 ... 2 GHz	400 / 450	56 / 58 ±2	20 / 20	2600	7 HU, 630 mm	55
<a href="#">BLMA 1020-450</a>	1 ... 2 GHz	450 / 500	56.5 / 59 ±2	20 / 20	3500	7 HU, 630 mm	55
<a href="#">BLMA 1020-550</a>	1 ... 2 GHz	550 / 600	57.4 / 60 ±2	20 / 20	4000	7 HU, 630 mm	60
<a href="#">BLMA 1020-600</a>	1 ... 2 GHz	600 / 700	57.8 / 60 ±2	15 / 20	4200	9 HU, 630 mm	105
<a href="#">BLMA 1020-750</a>	1 ... 2 GHz	750 / 900	58.8 / 61 ±2	20 / 20	6000	15 HU, 630 mm	150
<a href="#">BLMA 1020-850</a>	1 ... 2 GHz	850 / 1000	59.3 / 62 ±2	15 / 20	5000	9 HU, 630 mm	85
<a href="#">BLMA 1020-1400</a>	1 ... 2 GHz	1400 / 1500	61.5 / 64 ±2	20 / 20	12000	24 HU, 800 mm	250
<a href="#">BLMA 1020-2000</a>	1 ... 2 GHz	2000 / 2100	63 / 65 ±2	20 / 20	18000	41 HU, 800 mm	360
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1025-75</a>	1 ... 2.5 GHz	75 / 90	48.8 / 51 ±2	15 / 20	800	3 HU, 630 mm	22
<a href="#">BLMA 1025-150</a>	1 ... 2.5 GHz	150 / 180	51.8 / 54 ±2	15 / 20	1000	3 HU, 630 mm	26
<a href="#">BLMA 1025-200</a>	1 ... 2.5 GHz	200 / 250	53 / 55 ±2	15 / 20	1400	4 HU, 630 mm	32
<a href="#">BLMA 1025-250</a>	1 ... 2.5 GHz	250 / 350	54 / 56 ±2	18 / 20	2000	4 HU, 630 mm	38
<a href="#">BLMA 1025-500</a>	1 ... 2.5 GHz	500 / 650	57 / 59 ±2	18 / 20	3500	9 HU, 630 mm	88



<a href="#">BLMA 1025-1000</a>	1 ... 2.5 GHz	1000 / 1200	60 / 62 ±2	15 / 20	7000	12 HU, 800 mm	160
<a href="#">BLMA 1025-1500</a>	1 ... 2.5 GHz	1500 / 1800	61.8 / 64 ±2	15 / 20	14000	17 HU, 630 mm	210
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1030-1</a>	1 ... 3 GHz	1 / 1.3	30 / 32 ±2	20 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 1030-3</a>	1 ... 3 GHz	3 / 3.5	34.8 / 37 ±2	20 / 20	75	2 HU, 430 mm	12
<a href="#">BLMA 1030-5</a>	1 ... 3 GHz	5 / 6	37 / 39 ±2	20 / 20	75	2 HU, 430 mm	12
<a href="#">BLMA 1030-10</a>	1 ... 3 GHz	10 / 13	40 / 43 ±3	20 / 20	110	2 HU, 430 mm	13
<a href="#">BLMA 1030-20</a>	1 ... 3 GHz	20 / 25	43 / 45 ±2	15 / 20	200	2 HU, 430 mm	13
<a href="#">BLMA 1030-40</a>	1 ... 3 GHz	40 / 50	46 / 48 ±2	15 / 20	280	2 HU, 430 mm	13
<a href="#">BLMA 1030-80</a>	1 ... 3 GHz	80 / 100	49 / 51 ±2	15 / 20	450	3 HU, 430 mm	17
<a href="#">BLMA 1030-100</a>	1 ... 3 GHz	100 / 120	50 / 52 ±2	18 / 20	500	3 HU, 430 mm	17
<a href="#">BLMA 1030-150</a>	1 ... 3 GHz	150 / 200	51.8 / 54 ±2	15 / 20	1600	3 HU, 630 mm	24
<a href="#">BLMA 1030-200</a>	1 ... 3 GHz	200 / 230	53 / 55 ±2	15 / 20	1800	5 HU, 630 mm	42
<a href="#">BLMA 1030-250</a>	1 ... 3 GHz	250 / 300	54 / 56 ±2	20 / 20	3500	5 HU, 630 mm	56
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1032-1</a>	1 ... 3.2 GHz	1 / 1.3	30 / 32 ±2	20 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 1032-3</a>	1 ... 3.2 GHz	3 / 3.5	34.8 / 37 ±2	20 / 20	75	2 HU, 430 mm	12
<a href="#">BLMA 1032-5</a>	1 ... 3.2 GHz	5 / 6	37 / 39 ±2	20 / 20	75	2 HU, 430 mm	12
<a href="#">BLMA 1032-10</a>	1 ... 3.2 GHz	10 / 13	40 / 43 ±3	20 / 20	110	2 HU, 430 mm	13
<a href="#">BLMA 1032-20</a>	1 ... 3.2 GHz	20 / 25	43 / 45 ±2	15 / 20	200	2 HU, 430 mm	13
<a href="#">BLMA 1032-40</a>	1 ... 3.2 GHz	40 / 50	46 / 48 ±2	15 / 20	280	2 HU, 430 mm	13
<a href="#">BLMA 1032-80</a>	1 ... 3.2 GHz	80 / 100	49 / 51 ±2	15 / 20	450	3 HU, 430 mm	17
<a href="#">BLMA 1032-100</a>	1 ... 3.2 GHz	100 / 120	50 / 52 ±2	18 / 20	500	3 HU, 430 mm	17
<a href="#">BLMA 1032-150</a>	1 ... 3.2 GHz	160 / 200	51.8 / 54 ±2	15 / 20	1600	3 HU, 630 mm	29
<a href="#">BLMA 1032-200</a>	1 ... 3.2 GHz	200 / 230	53 / 55 ±2	15 / 20	1800	5 HU, 630 mm	42
<a href="#">BLMA 1032-250</a>	1 ... 3.2 GHz	250 / 300	54 / 56 ±2	20 / 20	3500	5 HU, 630 mm	56
<a href="#">BLMA 1032-500</a>	1 ... 3.2 GHz	500 / 600	57 / 59 ±2	15 / 20	7000	8 HU, 630 mm	50
<a href="#">BLMA 1032-1000/400</a>	1 ... 3.2 GHz 1 ... 2 GHz 2 ... 3.2 GHz	1000 / 1200 400 / 450	60 / 62 ±2 56 / 58 ±2	18 / 20 20 / 20	15000	18 HU, 800 mm	230
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1040-30/20D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	30 / 35 20 / 35	44.8 / 47 ±2 43 / 45 ±2	20 / 20 20 / 20	200	3 HU, 430 mm	19
<a href="#">BLMA 1040-30</a>	1 ... 4 GHz	30 / 35	44.8 / 47 ±2	15 / 20	300	2 HU, 430 mm	12
<a href="#">BLMA 1040-60/35D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	60 / 70 35 / 40	47.8 / 50 ±2 45.4 / 48 ±2	20 / 20 20 / 20	400	3 HU, 630 mm	22
<a href="#">BLMA 1040-60</a>	1 ... 4 GHz	60 / 80	47.8 / 50 ±2	18 / 20	600	3 HU, 430 mm	16
<a href="#">BLMA 1040-60D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	60 / 70 60 / 75	47.8 / 50 ±2 47.8 / 50 ±2	20 / 20 20 / 20	600	3 HU, 630 mm	26
<a href="#">BLMA 1040-100/60D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	100 / 120 60 / 75	50 / 52 ±2 47.8 / 50 ±2	20 / 20 20 / 20	750	3 HU, 630 mm	28
<a href="#">BLMA 1040-100D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	100 / 120 100 / 120	50 / 52 ±2 50 / 52 ±2	20 / 20 20 / 20	1300	6 HU, 630 mm	42
<a href="#">BLMA 1040-120</a>	1 ... 4 GHz	120 / 150	50.8 / 53 ±2	20 / 20	1500	3 HU, 630 mm	28
<a href="#">BLMA 1040-200/100D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	200 / 240 100 / 120	53 / 55 ±2 50 / 52 ±2	20 / 20 20 / 20	1300	6 HU, 630 mm	45
<a href="#">BLMA 1040-200</a>	1 ... 4 GHz	200 / 250	53 / 55 ±2	20 / 20	2100	5 HU, 630 mm	53
<a href="#">BLMA 1040-200D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	200 / 240 200 / 240	53 / 55 ±2 53 / 55 ±2	20 / 20 20 / 20	2500	9 HU, 630 mm	52
<a href="#">BLMA 1040-240/200D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	240 / 260 200 / 240	53.8 / 56 ±2 53 / 55 ±2	20 / 20 20 / 20	2700	9 HU, 630 mm	52
<a href="#">BLMA 1040-250</a>	1 ... 4 GHz	250 / 280	54 / 56 ±2	20 / 20	3000	5 HU, 630 mm	56
<a href="#">BLMA 1040-300/200D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	300 / 320 200 / 240	54.8 / 57 ±2 53 / 55 ±2	20 / 20 20 / 20	2700	9 HU, 630 mm	75
<a href="#">BLMA 1040-400/200D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	400 / 450 200 / 240	56 / 58 ±2 53 / 55 ±2	20 / 20 20 / 20	2700	13 HU, 630 mm	105
<a href="#">BLMA 1040-400</a>	1 ... 4 GHz	400 / 500	56 / 59 ±3	20 / 20	6000	7 HU, 630 mm	84
<a href="#">BLMA 1040-500</a>	1 ... 4 GHz	500 / 600	57 / 59 ±2	18 / 20	6000	8 HU, 630 mm	97
<a href="#">BLMA 1040-750/400D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	750 / 900 400 / 450	58.8 / 61 ±2 56 / 58 ±2	20 / 20 20 / 20	8000	41 HU, 800 mm	230
<a href="#">BLMA 1040-750</a>	1 ... 4 GHz	750 / 800	58.8 / 62 ±3	20 / 20	8000	12 HU, 800 mm	140
<a href="#">BLMA 1040-1000D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	1000 / 1200 1000 / 1200	60 / 62 ±2 60 / 62 ±2	20 / 20 20 / 20	8500	2x 24 HU, 800 mm	460

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1040-1300/400D</a>	1 ... 4 GHz 1 ... 2 GHz 2 ... 4 GHz	1300 / 1500 400 / 450	61.1 / 64 ±2 56 / 58 ±2	20 / 20 20 / 20	12000	37 HU, 800 mm	350
<a href="#">BLMA 1060-0.5</a>	1 ... 6 GHz	0.5 / 0.6	27 / 29 ±2	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 1060-1</a>	1 ... 6 GHz	1 / 1.2	30 / 32 ±2	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 1060-3</a>	1 ... 6 GHz	3 / 3.3	34.8 / 37 ±2	20 / 20	90	2 HU, 430 mm	11
<a href="#">BLMA 1060-6</a>	1 ... 6 GHz	6 / 10	37.8 / 40 ±2	20 / 20	180	2 HU, 430 mm	10
<a href="#">BLMA 1060-10</a>	1 ... 6 GHz	10 / 15	40 / 42 ±2	15 / 20	250	2 HU, 430 mm	12
<a href="#">BLMA 1060-15</a>	1 ... 6 GHz	15 / 20	41.8 / 45 ±3	15 / 20	250	2 HU, 430 mm	13
<a href="#">BLMA 1060-25</a>	1 ... 6 GHz	25 / 30	44 / 47 ±3	18 / 20	450	2 HU, 430 mm	13
<a href="#">BLMA 1060-30</a>	1 ... 6 GHz	30 / 35	44.8 / 48 ±3	18 / 20	500	2 HU, 430 mm	15
<a href="#">BLMA 1060-30D</a>	1 ... 6 GHz 1 ... 2 GHz 2 ... 6 GHz	30 / 35 30 / 35	44.8 / 47 ±2 44.8 / 47 ±2	20 / 20 20 / 20	450	3 HU, 430 mm	25
<a href="#">BLMA 1060-50</a>	1 ... 6 GHz	50 / 70	47 / 50 ±3	15 / 20	500	2 HU, 430 mm	13
<a href="#">BLMA 1060-75</a>	1 ... 6 GHz	75 / 80	48.8 / 52 ±3	15 / 20	950	3 HU, 430 mm	20
<a href="#">BLMA 1060-100/60/30D</a>	1 ... 6 GHz 1 ... 2 GHz 2 ... 4 GHz 4 ... 6 GHz	100 / 120 60 / 70 30 / 40	50 / 52 ±2 47.8 / 50 ±2 44.8 / 47 ±2	20 / 20 15 / 20 20 / 20	700	4 HU, 630 mm	38
<a href="#">BLMA 1060-100</a>	1 ... 6 GHz	100 / 120	50 / 53 ±3	15 / 20	950	3 HU, 430 mm	20
<a href="#">BLMA 1060-150/50D</a>	1 ... 6 GHz 1 ... 2.5 GHz 2.5 ... 6 GHz	150 / 180 50 / 60	51.8 / 55 ±2 47 / 49 ±2	15 / 20 15 / 20	1300	3 HU, 630 mm	25
<a href="#">BLMA 1060-150</a>	1 ... 6 GHz	150 / 180	51.8 / 55 ±2	15 / 20	2100	4 HU, 630 mm	40
<a href="#">BLMA 1060-200/100D</a>	1 ... 6 GHz 1 ... 2 GHz 2 ... 4 GHz 4 ... 6 GHz	200 / 240 180 / 240 100 / 120	53 / 55 ±2 53 / 55 ±2 50 / 52 ±2	20 / 20 20 / 20 20 / 20	1600	9 HU, 630 mm	82
<a href="#">BLMA 1060-200/100DS</a>	1 ... 6 GHz 1 ... 2.5 GHz 2.5 ... 6 GHz	200 / 240 100 / 120	53 / 55 ±2 50 / 52 ±2	15 / 20 15 / 20	1600	6 HU, 630 mm	65
<a href="#">BLMA 1060-200/150DS</a>	1 ... 6 GHz 1 ... 2.5 GHz 2.5 ... 6 GHz	200 / 230 150 / 180	53 / 55 ±2 51.8 / 54 ±2	20 / 20 20 / 20	1800	6 HU, 630 mm	58
<a href="#">BLMA 1060-200</a>	1 ... 6 GHz	200 / 220	53 / 56 ±3	18 / 20	3300	5 HU, 630 mm	59
<a href="#">BLMA 1060-200DS</a>	1 ... 6 GHz 1 ... 2.5 GHz 2.5 ... 6 GHz	200 / 240 200 / 240	53 / 55 ±2 53 / 55 ±2	20 / 20 15 / 20	3000	12 HU, 800 mm	110
<a href="#">BLMA 1060-250</a>	1 ... 6 GHz	250 / 280	54 / 57 ±3	15 / 20	4500	7 HU, 630 mm	84
<a href="#">BLMA 1060-300/150/100D</a>	1 ... 6 GHz 1 ... 2.5 GHz 2.5 ... 4 GHz 4 ... 6 GHz	300 / 320 150 / 170 100 / 120	54.8 / 57 ±2 51.8 / 54 ±2 50 / 52 ±2	20 / 20 15 / 20 20 / 20	2500	6 HU, 630 mm	67
<a href="#">BLMA 1060-400/100D</a>	1 ... 6 GHz 1 ... 4 GHz 4 ... 6 GHz	400 / 450 100 / 120	56 / 59 ±3 50 / 53 ±3	20 / 20 20 / 20	6500	8 HU, 630 mm	105
<a href="#">BLMA 1060-400</a>	1 ... 6 GHz	400 / 450	56 / 59 ±3	15 / 20	5000	10 HU, 630 mm	110
<a href="#">BLMA 1060-500</a>	1 ... 6 GHz	500 / 550	57 / 60 ±3	15 / 20	7000	12 HU, 800 mm	142
<a href="#">BLMA 1060-750</a>	1 ... 6 GHz	750 / 800	58.8 / 62 ±3	15 / 20	10000	18 HU, 800 mm	190
<a href="#">BLMA 1060-1000/300D</a>	1 ... 6 GHz 1 ... 3.2 GHz 3.2 ... 6 GHz	1000 / 1100 300 / 350	60 / 63 ±3 54.8 / 58 ±3	15 / 20 15 / 20	13500	32 HU, 800 mm	310
<a href="#">BLMA 1060-1000</a>	1 ... 6 GHz	1000 / 1100	60 / 63 ±3	15 / 20	15000	32 HU, 800 mm	350
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1012-4D</a>	1 ... 12 GHz 1 ... 6 GHz 6 ... 12 GHz	4 / 5 4 / 5	36 / 39 ±3 36 / 40 ±4	20 / 20 20 / 20	180	2 HU, 430 mm	13
<a href="#">BLMA 1012-7/5D</a>	1 ... 12 GHz 1 ... 6 GHz 6 ... 12 GHz	7 / 8 5 / 6	38.4 / 42 ±3 37 / 40 ±3	15 / 20 15 / 20	220	2 HU, 430 mm	14
<a href="#">BLMA 1012-10D</a>	1 ... 12 GHz 1 ... 6 GHz 6 ... 12 GHz	10 / 12 10 / 12	40 / 43 ±3 40 / 44 ±4	15 / 20 15 / 20	300	2 HU, 430 mm	14
<a href="#">BLMA 1012-15D</a>	1 ... 12 GHz 1 ... 6 GHz 6 ... 12 GHz	15 / 20 15 / 20	41.8 / 45 ±3 41.8 / 45 ±3	15 / 20 15 / 20	350	3 HU, 430 mm	19
<a href="#">BLMA 1012-20D</a>	1 ... 12 GHz 1 ... 6 GHz 6 ... 12 GHz	20 / 25 20 / 22	43 / 46 ±3 43 / 46 ±3	15 / 20 15 / 20	350	3 HU, 430 mm	20
<a href="#">BLMA 1012-30/10D</a>	1 ... 12 GHz 1 ... 6 GHz 6 ... 12 GHz	30 / 35 10 / 12	44.8 / 48 ±3 40 / 44 ±4	15 / 20 15 / 20	400	3 HU, 430 mm	20
<a href="#">BLMA 1012-30/15D</a>	1 ... 12 GHz 1 ... 6 GHz 6 ... 12 GHz	30 / 35 15 / 18	44.8 / 48 ±3 41.8 / 46 ±4	15 / 20 15 / 20	450	3 HU, 430 mm	23
<a href="#">BLMA 1012-30/20D</a>	1 ... 12 GHz 1 ... 6 GHz 6 ... 12 GHz	30 / 35 20 / 22	44.8 / 48 ±3 43 / 47 ±4	15 / 20 15 / 20	450	3 HU, 430 mm	23

<a href="#">BLMA 1012-50D</a>	1 ... 12 GHz 1 ... 6 GHz 6 ... 12 GHz	50 / 60 50 / 60	47 / 50 ±3 47 / 51 ±4	15 / 20 15 / 20	1300	5 HU, 630 mm	52
<a href="#">BLMA 1012-100D</a>	1 ... 12 GHz 1 ... 6 GHz 6 ... 12 GHz	100 / 110 100 / 110	50 / 53 ±3 50 / 54 ±4	15 / 20 15 / 20	2700	8 HU, 630 mm	85
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1018-0.5</a>	1 ... 18 GHz	0.5 / 0.6	27 / 30 ±3	20 / 20	40	2 HU, 430 mm	11
<a href="#">BLMA 1018-1</a>	1 ... 18 GHz	1 / 1.2	30 / 34 ±4	20 / 15	40	2 HU, 430 mm	12
<a href="#">BLMA 1018-1.5</a>	1 ... 18 GHz	1.5 / 1.8	31.8 / 35 ±3	15 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 1018-4</a>	1 ... 18 GHz	4 / 4.4	36 / 40 ±4	15 / 15	50	2 HU, 430 mm	12
<a href="#">BLMA 1018-4D</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	4 / 5 4 / 5	36 / 39 ±3 36 / 40 ±4	20 / 20 20 / 20	180	2 HU, 430 mm	13
<a href="#">BLMA 1018-7/5D</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	7 / 8 5 / 6	38.4 / 42 ±3 37 / 40 ±3	15 / 20 15 / 20	220	2 HU, 430 mm	14
<a href="#">BLMA 1018-10D</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	10 / 12 10 / 12	40 / 43 ±3 40 / 44 ±4	15 / 20 15 / 20	300	2 HU, 430 mm	14
<a href="#">BLMA 1018-15D</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	15 / 20 15 / 20	41.8 / 45 ±3 41.8 / 45 ±3	15 / 20 15 / 20	350	3 HU, 430 mm	19
<a href="#">BLMA 1018-20D</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	20 / 25 20 / 22	43 / 46 ±3 43 / 46 ±3	15 / 20 15 / 20	350	3 HU, 430 mm	20
<a href="#">BLMA 1018-30/10D</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 16 GHz 16 ... 18 GHz	30 / 35 10 / 12 8 / 10	44.8 / 48 ±3 40 / 44 ±4 39 / 43 ±4	15 / 20 15 / 20 15 / 20	400	3 HU, 430 mm	20
<a href="#">BLMA 1018-30/15D</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	30 / 35 15 / 18	44.8 / 48 ±3 41.8 / 46 ±4	15 / 20 15 / 20	450	3 HU, 430 mm	23
<a href="#">BLMA 1018-30/20D</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	30 / 35 20 / 22	44.8 / 48 ±3 43 / 47 ±4	15 / 20 15 / 20	450	3 HU, 430 mm	23
<a href="#">BLMA 1018-50D</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	50 / 60 50 / 60	47 / 50 ±3 47 / 51 ±4	15 / 20 15 / 20	1300	5 HU, 630 mm	52
<a href="#">BLMA 1018-100D</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	100 / 110 100 / 110	50 / 53 ±3 50 / 54 ±4	15 / 20 15 / 20	2700	8 HU, 630 mm	85
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1026-2D</a>	1 ... 26.5 GHz 1 ... 18 GHz 18 ... 26.5 GHz	2 / 3 2 / 2.2	33 / 36 ±3 33 / 36 ±3	15 / 20 20 / 20	150	2 HU, 430 mm	15
<a href="#">BLMA 1026-40/4D</a>	1 ... 26.5 GHz 1 ... 6 GHz 6 ... 18 GHz 18 ... 26.5 GHz	40 / 45 35 / 38 4 / 4.5	46 / 49 ±3 45.4 / 49 ±3 36 / 39 ±3	15 / 20 15 / 20 20 / 20	900	4 HU, 630 mm	38
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1214-500</a>	1.2 ... 1.4 GHz	500 / 550	57 / 59 ±2	20 / 20	1850	4 HU, 630 mm	37
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2040-1</a>	2 ... 4 GHz	1 / 1.3	30 / 32 ±2	20 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 2040-2</a>	2 ... 4 GHz	2 / 2.5	33 / 35 ±2	20 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 2040-7</a>	2 ... 4 GHz	7 / 9	38.5 / 41 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 2040-20</a>	2 ... 4 GHz	20 / 25	43 / 45 ±2	20 / 20	200	2 HU, 430 mm	15
<a href="#">BLMA 2040-35</a>	2 ... 4 GHz	35 / 45	45.4 / 48 ±2	20 / 20	400	3 HU, 630 mm	22
<a href="#">BLMA 2040-60</a>	2 ... 4 GHz	60 / 75	47.8 / 50 ±2	20 / 20	600	3 HU, 630 mm	26
<a href="#">BLMA 2040-80S</a>	2 ... 4 GHz	80 / 100	49 / 51 ±2	15 / 20	650	3 HU, 630 mm	21
<a href="#">BLMA 2040-110</a>	2 ... 4 GHz	110 / 130	50.4 / 53 ±2	20 / 20	1100	3 HU, 630 mm	27
<a href="#">BLMA 2040-200</a>	2 ... 4 GHz	200 / 240	53 / 55 ±2	20 / 20	2500	6 HU, 630 mm	45
<a href="#">BLMA 2040-300</a>	2 ... 4 GHz	300 / 350	54.8 / 57 ±2	20 / 20	4000	12 HU, 800 mm	120
<a href="#">BLMA 2040-400</a>	2 ... 4 GHz	400 / 450	56 / 58 ±2	20 / 20	7000	8 HU, 630 mm	88
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2060-0.5</a>	2 ... 6 GHz	0.5 / 0.6	27 / 29 ±2	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 2060-1</a>	2 ... 6 GHz	1 / 1.2	30 / 32 ±2	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 2060-3</a>	2 ... 6 GHz	3 / 3.3	34.8 / 37 ±2	20 / 20	90	2 HU, 430 mm	11
<a href="#">BLMA 2060-6</a>	2 ... 6 GHz	6 / 10	37.8 / 40 ±2	18 / 20	120	2 HU, 430 mm	12
<a href="#">BLMA 2060-10</a>	2 ... 6 GHz	10 / 12	40 / 42 ±2	18 / 20	150	2 HU, 430 mm	12
<a href="#">BLMA 2060-10S</a>	2 ... 6 GHz	10 / 12	40 / 42 ±2	15 / 20	150	2 HU, 430 mm	12
<a href="#">BLMA 2060-15</a>	2 ... 6 GHz	15 / 20	42 / 44 ±2	15 / 20	250	2 HU, 430 mm	14
<a href="#">BLMA 2060-25</a>	2 ... 6 GHz	25 / 35	44.8 / 48 ±3	15 / 20	400	2 HU, 430 mm	13

<a href="#">BLMA 2060-30</a>	2 ... 6 GHz	30 / 40	44.8 / 47 ±2	18 / 20	500	2 HU, 430 mm	14
<a href="#">BLMA 2060-50</a>	2 ... 6 GHz	50 / 60	47 / 50 ±3	15 / 20	550	2 HU, 430 mm	13
<a href="#">BLMA 2060-75</a>	2 ... 6 GHz	75 / 80	48.8 / 52 ±3	15 / 20	800	3 HU, 430 mm	19
<a href="#">BLMA 2060-100</a>	2 ... 6 GHz	100 / 120	50 / 53 ±3	20 / 20	1100	3 HU, 430 mm	19
<a href="#">BLMA 2060-200</a>	2 ... 6 GHz	200 / 230	53 / 56 ±3	15 / 20	2200	5 HU, 630 mm	37
<a href="#">BLMA 2060-250</a>	2 ... 6 GHz	250 / 280	54 / 57 ±3	15 / 20	2800	5 HU, 630 mm	44
<a href="#">BLMA 2060-350</a>	2 ... 6 GHz	350 / 400	55.4 / 59 ±3	15 / 20	4000	6 HU, 630 mm	56
<a href="#">BLMA 2060-500</a>	2 ... 6 GHz	500 / 550	57 / 60 ±3	15 / 20	6500	15 HU, 800 mm	170
<a href="#">BLMA 2060-1000</a>	2 ... 6 GHz	1000 / 1100	60 / 63 ±3	15 / 20	14000	32 HU, 800 mm	350

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2080-0.5</a>	2 ... 8 GHz	0.5 / 0.6	27 / 29 ±2	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 2080-1</a>	2 ... 8 GHz	1 / 1.2	30 / 32 ±2	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 2080-2</a>	2 ... 8 GHz	2 / 2.3	33 / 35 ±2	20 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 2080-8</a>	2 ... 8 GHz	8 / 10	39 / 41 ±2	15 / 20	100	2 HU, 430 mm	12
<a href="#">BLMA 2080-10</a>	2 ... 8 GHz	10 / 12	40 / 44 ±4	18 / 20	175	2 HU, 430 mm	10
<a href="#">BLMA 2080-20</a>	2 ... 8 GHz	20 / 22	43 / 45 ±2	15 / 20	550	3 HU, 430 mm	19
<a href="#">BLMA 2080-30</a>	2 ... 8 GHz	30 / 33	44.8 / 47 ±2	15 / 20	750	3 HU, 430 mm	22
<a href="#">BLMA 2080-60</a>	2 ... 8 GHz	60 / 66	47.8 / 50 ±2	15 / 20	1600	4 HU, 630 mm	38

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2012-5</a>	2 ... 12 GHz	5 / 6	37 / 40 ±3	15 / 20	100	2 HU, 430 mm	12
<a href="#">BLMA 2012-10</a>	2 ... 12 GHz	10 / 12	40 / 43 ±3	12 / 20	200	2 HU, 430 mm	12

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2018-0.2</a>	2 ... 18 GHz	0.2 / 0.25	23 / 25 ±2	20 / 20	45	2 HU, 430 mm	9
<a href="#">BLMA 2018-0.3</a>	2 ... 18 GHz	0.3 / 0.35	24.8 / 27 ±2	20 / 20	45	2 HU, 430 mm	9
<a href="#">BLMA 2018-0.5</a>	2 ... 18 GHz	0.5 / 0.8	27 / 29 ±2	18 / 20	45	2 HU, 430 mm	9
<a href="#">BLMA 2018-0.8</a>	2 ... 18 GHz	0.8 / 1	29 / 32 ±3	20 / 20	45	2 HU, 430 mm	9
<a href="#">BLMA 2018-1</a>	2 ... 18 GHz	1 / 1.2	30 / 34 ±4	18 / 20	45	2 HU, 430 mm	9
<a href="#">BLMA 2018-1.5</a>	2 ... 18 GHz	1.5 / 1.8	31 / 34 ±3	15 / 20	75	2 HU, 430 mm	10
<a href="#">BLMA 2018-2</a>	2 ... 18 GHz	2 / 2.2	33 / 35 ±2	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 2018-4</a>	2 ... 18 GHz	4 / 4.5	36 / 39 ±3	15 / 20	150	2 HU, 430 mm	12
<a href="#">BLMA 2018-7.5</a>	2 ... 18 GHz				200	2 HU, 430 mm	12
	2 ... 17 GHz	7.5 / 8	38 / 41 ±3	12 / 15			
	17 ... 18 GHz	6.3 / 7.5	38 / 41 ±3	20 / 20			
<a href="#">BLMA 2018-30</a>	2 ... 18 GHz	30 / 35	44.8 / 48 ±3	15 / 20	850	3 HU, 430 mm	21
<a href="#">BLMA 2018-20D</a>	2 ... 18 GHz				350	3 HU, 430 mm	23
	2 ... 6 GHz	20 / 25	43 / 45 ±2	20 / 20			
	6 ... 18 GHz	20 / 22	43 / 46 ±3	15 / 20			

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2020-0.8</a>	2 ... 20 GHz	0.8 / 1	29 / 32 ±3	15 / 20	100	2 HU, 430 mm	10
<a href="#">BLMA 2020-1</a>	2 ... 20 GHz	1 / 1.2	30 / 33 ±3	18 / 20	100	2 HU, 430 mm	9
<a href="#">BLMA 2020-1.5</a>	2 ... 20 GHz	1.5 / 1.8	31 / 35 ±3	15 / 20	120	2 HU, 430 mm	10
<a href="#">BLMA 2020-2</a>	2 ... 20 GHz	2 / 2.2	33 / 36 ±3	15 / 20	120	2 HU, 430 mm	11
<a href="#">BLMA 2020-3</a>	2 ... 20 GHz	3 / 3.5	34.8 / 38 ±3	15 / 20	200	2 HU, 430 mm	11
<a href="#">BLMA 2020-4</a>	2 ... 20 GHz	4 / 5	36 / 40 ±4	15 / 20	200	2 HU, 430 mm	15
<a href="#">BLMA 2020-10</a>	2 ... 20 GHz	10 / 14	40 / 44 ±4	15 / 20	400	2 HU, 430 mm	15
<a href="#">BLMA 2020-20</a>	2 ... 20 GHz	20 / 22	43 / 47 ±4	15 / 20	600	3 HU, 430 mm	18

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 3060-200</a>	3 ... 6 GHz	200 / 220	53 / 56 ±3	15 / 20	2500	4 HU, 630 mm	37

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 4060-2</a>	4 ... 6 GHz	2 / 2.5	33 / 35 ±2	20 / 20	75	2 HU, 430 mm	10
<a href="#">BLMA 4060-4</a>	4 ... 6 GHz	4 / 4.5	36 / 38 ±2	20 / 20	80	2 HU, 430 mm	10
<a href="#">BLMA 4060-10</a>	4 ... 6 GHz	10 / 11	40 / 42 ±2	20 / 20	150	2 HU, 430 mm	10
<a href="#">BLMA 4060-20</a>	4 ... 6 GHz	20 / 22	43 / 45 ±2	20 / 20	300	2 HU, 430 mm	13
<a href="#">BLMA 4060-40</a>	4 ... 6 GHz	40 / 45	46 / 48 ±2	20 / 20	350	2 HU, 430 mm	13
<a href="#">BLMA 4060-50</a>	4 ... 6 GHz	50 / 60	47 / 49 ±2	20 / 20	500	2 HU, 430 mm	13
<a href="#">BLMA 4060-100</a>	4 ... 6 GHz	100 / 120	50 / 53 ±3	20 / 20	1050	3 HU, 430 mm	28
<a href="#">BLMA 4060-200</a>	4 ... 6 GHz	200 / 230	53 / 55 ±2	20 / 20	2500	4 HU, 630 mm	37
<a href="#">BLMA 4060-400</a>	4 ... 6 GHz	400 / 450	56 / 58 ±2	20 / 20	6000	8 HU, 630 mm	88
<a href="#">BLMA 4060-850</a>	4 ... 6 GHz	850 / 900	59.3 / 60 ±2	20 / 20	13000	15 HU, 800 mm	200

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 4080-1</a>	4 ... 8 GHz	1 / 1.2	30 / 32 ±2	20 / 20	40	2 HU, 430 mm	11
<a href="#">BLMA 4080-2</a>	4 ... 8 GHz	2 / 2.3	33 / 35 ±2	20 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 4080-3</a>	4 ... 8 GHz	3 / 3.5	34.8 / 38 ±3	20 / 20	110	2 HU, 430 mm	12

<a href="#">BLMA 4080-5</a>	4 ... 8 GHz	5 / 6	37 / 40 ±3	20 / 20	150	2 HU, 430 mm	12
<a href="#">BLMA 4080-7</a>	4 ... 8 GHz	7 / 8	38.5 / 42 ±3	15 / 20	200	2 HU, 430 mm	12
<a href="#">BLMA 4080-10</a>	4 ... 8 GHz	10 / 12	40 / 43 ±3	20 / 20	300	2 HU, 430 mm	13
<a href="#">BLMA 4080-20</a>	4 ... 8 GHz	20 / 22	43 / 46 ±3	20 / 20	550	3 HU, 430 mm	19
<a href="#">BLMA 4080-30</a>	4 ... 8 GHz	30 / 40	44.8 / 48 ±3	20 / 20	750	3 HU, 430 mm	22
<a href="#">BLMA 4080-60</a>	4 ... 8 GHz	60 / 70	47.8 / 51 ±3	20 / 20	1600	4 HU, 630 mm	38
<a href="#">BLMA 4080-100</a>	4 ... 8 GHz	100 / 110	50 / 53 ±3	20 / 20	2500	5 HU, 630 mm	45

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
-------	-----------------	---	-------------------------	-------------------------------	------------------	------------------------------------	--------------

<a href="#">BLMA 4010-0.5</a>	4 ... 10 GHz	0.5 / 0.6	27 / 29 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 4010-1</a>	4 ... 10 GHz	1 / 1.2	30 / 32 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 4010-2</a>	4 ... 10 GHz	2 / 2.3	33 / 35 ±2	20 / 20	90	2 HU, 430 mm	11
<a href="#">BLMA 4010-6</a>	4 ... 10 GHz	6 / 6.5	37.8 / 40 ±2	20 / 20	200	2 HU, 430 mm	13

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
-------	-----------------	---	-------------------------	-------------------------------	------------------	------------------------------------	--------------

<a href="#">BLMA 4012-2</a>	4 ... 12 GHz	2 / 2.5	33 / 36 ±3	15 / 20	100	2 HU, 430 mm	10
<a href="#">BLMA 4012-5</a>	4 ... 12 GHz	5 / 6	37 / 40 ±3	15 / 20	120	2 HU, 430 mm	13
<a href="#">BLMA 4012-10</a>	4 ... 12 GHz	10 / 11	40 / 43 ±3	20 / 20	300	2 HU, 430 mm	13

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
-------	-----------------	---	-------------------------	-------------------------------	------------------	------------------------------------	--------------

<a href="#">BLMA 4018-5</a>	4 ... 18 GHz	5 / 6	37 / 39 ±2	18 / 20	200	2 HU, 430 mm	12
<a href="#">BLMA 4018-10</a>	4 ... 18 GHz	10 / 12	40 / 44 ±4	18 / 18	300	2 HU, 430 mm	13
<a href="#">BLMA 4018-20/15D</a>	4 ... 18 GHz				380	3 HU, 430 mm	21

	4 ... 6 GHz	20 / 25	43 / 45 ±2	20 / 20			
	6 ... 18 GHz	15 / 18	41.8 / 46 ±4	15 / 20			
<a href="#">BLMA 4018-20D</a>	4 ... 18 GHz				400	3 HU, 430 mm	23
	4 ... 6 GHz	20 / 25	43 / 45 ±2	20 / 20			
	6 ... 18 GHz	20 / 22	43 / 46 ±3	15 / 20			

<a href="#">BLMA 4018-30D</a>	4 ... 18 GHz				700	4 HU, 630 mm	37
	4 ... 6 GHz	30 / 35	44.8 / 47 ±2	20 / 20			
	6 ... 18 GHz	30 / 35	44.8 / 47 ±3	15 / 20			

<a href="#">BLMA 4018-40/35D</a>	4 ... 18 GHz				700	4 HU, 630 mm	37
	4 ... 6 GHz	40 / 45	46 / 48 ±2	20 / 20			
	6 ... 18 GHz	35 / 40	45.4 / 48 ±3	15 / 20			

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
-------	-----------------	---	-------------------------	-------------------------------	------------------	------------------------------------	--------------

<a href="#">BLMA 6080-30</a>	6 ... 8 GHz	30 / 33	44.8 / 47 ±2	20 / 20	750	3 HU, 430 mm	22
<a href="#">BLMA 6080-60</a>	6 ... 8 GHz	60 / 66	47.8 / 50 ±2	20 / 20	1000	4 HU, 630 mm	38

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
-------	-----------------	---	-------------------------	-------------------------------	------------------	------------------------------------	--------------

<a href="#">BLMA 6010-5</a>	6 ... 10 GHz	5 / 6	37 / 40 ±3	15 / 20	200	2 HU, 430 mm	13
-----------------------------	--------------	-------	------------	---------	-----	--------------	----

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
-------	-----------------	---	-------------------------	-------------------------------	------------------	------------------------------------	--------------

<a href="#">BLMA 6012-0.5</a>	6 ... 12 GHz	0.5 / 0.6	27 / 29 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 6012-1</a>	6 ... 12 GHz	1 / 1.2	30 / 32 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 6012-2</a>	6 ... 12 GHz	2 / 2.3	33 / 35 ±2	20 / 20	90	2 HU, 430 mm	11
<a href="#">BLMA 6012-5</a>	6 ... 12 GHz	5 / 6	37 / 39 ±2	15 / 20	150	2 HU, 430 mm	12
<a href="#">BLMA 6012-10</a>	6 ... 12 GHz	10 / 11	40 / 42 ±2	15 / 20	300	2 HU, 430 mm	13
<a href="#">BLMA 6012-20</a>	6 ... 12 GHz	20 / 22	43 / 45 ±2	15 / 20	450	3 HU, 430 mm	14
<a href="#">BLMA 6012-35</a>	6 ... 12 GHz	35 / 40	45.4 / 49 ±3	12 / 20	550	3 HU, 430 mm	19
<a href="#">BLMA 6012-60</a>	6 ... 12 GHz	60 / 65	47.8 / 51 ±3	15 / 20	1000	3 HU, 630 mm	24

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
-------	-----------------	---	-------------------------	-------------------------------	------------------	------------------------------------	--------------

<a href="#">BLMA 6018-0.5</a>	6 ... 18 GHz	0.5 / 0.6	27 / 29 ±2	20 / 20	40	2 HU, 430 mm	11
<a href="#">BLMA 6018-1</a>	6 ... 18 GHz	1 / 1.2	30 / 32 ±2	20 / 20	40	2 HU, 430 mm	11
<a href="#">BLMA 6018-2</a>	6 ... 18 GHz	2 / 2.3	33 / 35 ±2	15 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 6018-4</a>	6 ... 18 GHz	4 / 5	36 / 39 ±3	15 / 20	150	2 HU, 430 mm	11
<a href="#">BLMA 6018-5</a>	6 ... 18 GHz	5 / 6	37 / 40 ±3	15 / 20	160	2 HU, 430 mm	11
<a href="#">BLMA 6018-7</a>	6 ... 18 GHz	7 / 8	38.5 / 43 ±4	15 / 20	200	2 HU, 430 mm	11
<a href="#">BLMA 6018-10</a>	6 ... 18 GHz	10 / 13	40 / 44 ±4	15 / 20	220	2 HU, 430 mm	13
<a href="#">BLMA 6018-15</a>	6 ... 18 GHz	20 / 18	41.8 / 46 ±4	15 / 20	400	2 HU, 430 mm	14
<a href="#">BLMA 6018-20</a>	6 ... 18 GHz	20 / 22	43 / 47 ±4	18 / 20	400	2 HU, 430 mm	14
<a href="#">BLMA 6018-35</a>	6 ... 18 GHz	35 / 40	45.4 / 50 ±4	18 / 20	800	3 HU, 430 mm	21
<a href="#">BLMA 6018-60</a>	6 ... 18 GHz	60 / 65	47.8 / 52 ±4	18 / 20	1250	4 HU, 630 mm	39
<a href="#">BLMA 6018-100</a>	6 ... 18 GHz	100 / 110	50 / 54 ±4	18 / 20	2500	6 HU, 630 mm	72

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
-------	-----------------	---	-------------------------	-------------------------------	------------------	------------------------------------	--------------

<a href="#">BLMA 6020-10</a>	6 ... 20 GHz	10 / 12	40 / 43 ±3	15 / 20	250	2 HU, 430 mm	12
<a href="#">BLMA 6020-20</a>	6 ... 20 GHz	20 / 25	43 / 46 ±3	15 / 20	400	3 HU, 430 mm	19

Model	Frequency Range	Output Power	Gain	Harmonics	Line Power	Dimensions	Weight
-------	-----------------	--------------	------	-----------	------------	------------	--------

		P <sub>N</sub> min / typ W	min / typ dB	2nd / 3rd dBc	VA	(H, D) 19"-System	kg
<a href="#">BLMA 8012-1</a>	8 ... 12 GHz	1 / 1.2	30 / 32 ±2	20 / 20	30	2 HU, 430 mm	9
<a href="#">BLMA 8012-2</a>	8 ... 12 GHz	2 / 2.3	33 / 35 ±2	20 / 20	70	2 HU, 430 mm	10
<a href="#">BLMA 8012-4</a>	8 ... 12 GHz	4 / 4.5	36 / 38 ±2	20 / 20	80	2 HU, 430 mm	10
<a href="#">BLMA 8012-5</a>	8 ... 12 GHz	5 / 6	37 / 39 ±2	20 / 20	90	2 HU, 430 mm	11
<a href="#">BLMA 8012-10</a>	8 ... 12 GHz	10 / 13	40 / 42 ±2	20 / 20	125	2 HU, 430 mm	11
<a href="#">BLMA 8012-15</a>	8 ... 12 GHz	15 / 20	41.8 / 44 ±2	20 / 20	150	2 HU, 430 mm	12
<a href="#">BLMA 8012-20</a>	8 ... 12 GHz	20 / 25	43 / 46 ±3	20 / 20	450	2 HU, 430 mm	12
<a href="#">BLMA 8012-25</a>	8 ... 12 GHz	25 / 35	44 / 47 ±3	20 / 20	500	2 HU, 430 mm	17
<a href="#">BLMA 8012-40</a>	8 ... 12 GHz	40 / 45	46 / 49 ±3	20 / 20	500	3 HU, 430 mm	17
<a href="#">BLMA 8012-80</a>	8 ... 12 GHz	80 / 90	49 / 53 ±4	20 / 20	1000	3 HU, 430 mm	18
<a href="#">BLMA 8012-150</a>	8 ... 12 GHz	150 / 160	51.8 / 55 ±3	20 / 20	2000	5 HU, 630 mm	48

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 8018-0.5</a>	8 ... 18 GHz	0.5 / 0.6	27 / 29 ±2	20 / 20	40	2 HU, 430 mm	10
<a href="#">BLMA 8018-1</a>	8 ... 18 GHz	1 / 1.2	30 / 32 ±2	20 / 20	40	2 HU, 430 mm	10
<a href="#">BLMA 8018-1.5</a>	8 ... 18 GHz	1.5 / 1.7	31.8 / 34 ±2	20 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 8018-2</a>	8 ... 18 GHz	2 / 2.3	33 / 35 ±2	18 / 20	75	2 HU, 430 mm	11
<a href="#">BLMA 8018-5</a>	8 ... 18 GHz	5 / 6	37 / 39 ±2	15 / 20	150	2 HU, 430 mm	12
<a href="#">BLMA 8018-7</a>	8 ... 18 GHz	7 / 8	38.5 / 41 ±2	20 / 20	200	2 HU, 430 mm	12
<a href="#">BLMA 8018-10</a>	8 ... 18 GHz	10 / 11	40 / 43 ±3	15 / 20	200	2 HU, 430 mm	12
<a href="#">BLMA 8018-20</a>	8 ... 18 GHz	20 / 22	43 / 47 ±4	15 / 20	350	2 HU, 430 mm	14
<a href="#">BLMA 8018-35</a>	8 ... 18 GHz	35 / 40	45.4 / 50 ±4	20 / 20	800	3 HU, 430 mm	20
<a href="#">BLMA 8018-70</a>	8 ... 18 GHz	70 / 75	48.4 / 53 ±4	20 / 20	1250	4 HU, 630 mm	39
<a href="#">BLMA 8018-100</a>	8 ... 18 GHz	100 / 110	50 / 53 ±3	20 / 20	2500	6 HU, 630 mm	55

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1218-1</a>	12 ... 18 GHz	1 / 1.2	30 / 32 ±2	20 / 20	40	2 HU, 430 mm	11
<a href="#">BLMA 1218-2</a>	12 ... 18 GHz	2 / 2.3	33 / 35 ±2	20 / 20	60	2 HU, 430 mm	11
<a href="#">BLMA 1218-5</a>	12 ... 18 GHz	5 / 6	37 / 40 ±3	20 / 20	120	2 HU, 430 mm	11
<a href="#">BLMA 1218-7</a>	12 ... 18 GHz	7 / 8	38.5 / 42 ±3	20 / 20	200	2 HU, 430 mm	12
<a href="#">BLMA 1218-10</a>	12 ... 18 GHz	10 / 11	40 / 43 ±3	15 / 20	250	2 HU, 430 mm	13
<a href="#">BLMA 1218-20</a>	12 ... 18 GHz	20 / 22	43 / 46 ±3	15 / 20	350	2 HU, 430 mm	14

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1826-0.25</a>	18 ... 26.5 GHz	0.25 / 0.28	24 / 26 ±2	20 / 20	50	2 HU, 430 mm	9
<a href="#">BLMA 1826-0.5</a>	18 ... 26.5 GHz	0.5 / 0.6	27 / 29 ±2	20 / 20	50	2 HU, 430 mm	9
<a href="#">BLMA 1826-0.7</a>	18 ... 26.5 GHz	0.7 / 0.8	28.5 / 31 ±2	20 / 20	50	2 HU, 430 mm	9
<a href="#">BLMA 1826-1</a>	18 ... 26.5 GHz	1 / 1.1	30 / 32 ±2	20 / 20	50	2 HU, 430 mm	9
<a href="#">BLMA 1826-2</a>	18 ... 26.5 GHz	2 / 2.2	33 / 35 ±2	20 / 20	75	2 HU, 430 mm	9
<a href="#">BLMA 1826-3</a>	18 ... 26.5 GHz	3 / 3.3	34.8 / 38 ±3	20 / 20	120	2 HU, 430 mm	10
<a href="#">BLMA 1826-4</a>	18 ... 26.5 GHz	4 / 4.4	36 / 40 ±4	20 / 20	150	2 HU, 430 mm	11
<a href="#">BLMA 1826-5</a>	18 ... 26.5 GHz	5 / 6	37 / 41 ±4	20 / 20	150	2 HU, 430 mm	13
<a href="#">BLMA 1826-10</a>	18 ... 26.5 GHz	10 / 12	40 / 44 ±4	20 / 20	300	2 HU, 430 mm	15

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 1840-0.1</a>	18 ... 40 GHz	0.1 / 0.12	20 / 23 ±3	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 1840-0.2</a>	18 ... 40 GHz	0.2 / 0.22	23 / 26 ±3	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 1840-0.3</a>	18 ... 40 GHz	0.3 / 0.35	25 / 28 ±3	20 / 20	50	2 HU, 430 mm	10
<a href="#">BLMA 1840-0.5</a>	18 ... 40 GHz	0.5 / 0.6	27 / 30 ±3	20 / 20	70	2 HU, 430 mm	10
<a href="#">BLMA 1840-0.7</a>	18 ... 40 GHz				70	2 HU, 430 mm	9
	18 ... 20 GHz	0.5 / 0.7	28 / 32 ±4	20 / 20			
	20 ... 40 GHz	0.7 / 0.8	28.5 / 33 ±4	20 / 20			
<a href="#">BLMA 1840-1</a>	18 ... 40 GHz				100	2 HU, 430 mm	10
	18 ... 20 GHz	0.8 / 1	29 / 32 ±3	20 / 20			
	20 ... 40 GHz	1 / 1.1	30 / 33 ±3	20 / 20			
<a href="#">BLMA 1840-1D</a>	18 ... 40 GHz				100	2 HU, 430 mm	10
	18 ... 26.5 GHz	1 / 1.2	30 / 33 ±3	20 / 20			
	26.5 ... 40 GHz	1 / 1.2	30 / 33 ±3	20 / 20			
<a href="#">BLMA 1840-2/1.5D</a>	18 ... 40 GHz				150	2 HU, 430 mm	11
	18 ... 26.5 GHz	2 / 2.2	33 / 36 ±3	20 / 20			
	26.5 ... 40 GHz	1.5 / 1.8	31.8 / 35 ±3	20 / 20			
<a href="#">BLMA 1840-2D</a>	18 ... 40 GHz				150	2 HU, 430 mm	11
	18 ... 26.5 GHz	2 / 2.2	33 / 36 ±3	20 / 20			
	26.5 ... 31 GHz	2 / 2.2	33 / 36 ±3	20 / 20			
	31 ... 38 GHz	2 / 2.2	33 / 36 ±3	20 / 20			
	38 ... 40 GHz	1.4 / 1.7	30 / 33 ±3	20 / 20			

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2631-2</a>	26.5 ... 31 GHz	2 / 2.5	33 / 36 ±3	20 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 2631-4</a>	26.5 ... 31 GHz	4 / 4.5	36 / 40 ±4	20 / 20	150	2 HU, 430 mm	12
<a href="#">BLMA 2631-5</a>	26.5 ... 31 GHz	5 / 5.5	37 / 41 ±4	20 / 20	150	2 HU, 430 mm	12
<a href="#">BLMA 2631-10</a>	26.5 ... 31 GHz	10 / 11	40 / 44 ±4	20 / 20	300	2 HU, 430 mm	13



Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 2640-0.1</a>	26.5 ... 40 GHz	0.1 / 0.12	20 / 23 ±3	20 / 20	50	2 HU, 430 mm	9
<a href="#">BLMA 2640-0.2</a>	26.5 ... 40 GHz	0.2 / 0.23	23 / 26 ±3	20 / 20	50	2 HU, 430 mm	9
<a href="#">BLMA 2640-0.3</a>	26.5 ... 40 GHz	0.3 / 0.35	25 / 28 ±3	20 / 20	90	2 HU, 430 mm	9
<a href="#">BLMA 2640-0.5</a>	26.5 ... 40 GHz	0.5 / 0.6	27 / 30 ±3	20 / 20	90	2 HU, 430 mm	10
<a href="#">BLMA 2640-0.8</a>	26.5 ... 40 GHz	0.8 / 1	29 / 32 ±3	20 / 20	90	2 HU, 430 mm	10
<a href="#">BLMA 2640-1</a>	26.5 ... 40 GHz	1 / 1.1	30 / 34 ±4	20 / 20	110	2 HU, 430 mm	11
<a href="#">BLMA 2640-1.5</a>	26.5 ... 40 GHz	1.5 / 1.6	31.8 / 36 ±4	20 / 20	120	2 HU, 430 mm	12
<a href="#">BLMA 2640-2</a>	26.5 ... 40 GHz 26.5 ... 36 GHz 36 ... 40 GHz	2 / 2.1 1.6 / 1.8	33 / 37 ±4 32 / 36 ±4	20 / 20 20 / 20	150	2 HU, 430 mm	12
<a href="#">BLMA 2640-4D</a>	26.5 ... 40 GHz 26.5 ... 31 GHz 31 ... 40 GHz	4 / 4.5 4 / 4.25	36 / 40 ±4 36 / 40 ±4	20 / 20 20 / 20	300	2 HU, 430 mm	13
<a href="#">BLMA 2640-5</a>	26.5 ... 40 GHz	5 / 5.25	37 / 41 ±4	20 / 20	300	2 HU, 430 mm	14
<a href="#">BLMA 2640-5D</a>	26.5 ... 40 GHz 26.5 ... 31 GHz 31 ... 40 GHz	5 / 5.25 5 / 5.25	37 / 41 ±4 37 / 41 ±4	20 / 20 20 / 20	300	2 HU, 430 mm	14
<a href="#">BLMA 2640-10D</a>	26.5 ... 40 GHz 26.5 ... 31 GHz 31 ... 40 GHz	10 / 11 10 / 11	40 / 44 ±4 40 / 44 ±4	20 / 20 20 / 20	450	3 HU, 430 mm	18

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BLMA 3140-2</a>	31 ... 40 GHz	2 / 2.5	33 / 36 ±3	20 / 20	50	2 HU, 430 mm	11
<a href="#">BLMA 3140-4</a>	31 ... 40 GHz	4 / 4.5	36 / 39 ±3	20 / 20	250	2 HU, 430 mm	12
<a href="#">BLMA 3140-10</a>	31 ... 40 GHz	10 / 11	40 / 44 ±4	20 / 20	450	2 HU, 430 mm	13

## TWAL

Anzahl Modellreihen: 22

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0103-250</a>	1 ... 2.5 GHz	250 / 300	54 / 62 ±7.5	4 / 12	3000	5 HU, 660 mm	48
<a href="#">TWAL 0103-500</a>	1 ... 2.5 GHz	500 / 600	54 / 62 ±7.5	2 / 10	4000	15 HU, 800 mm	140
<a href="#">TWAL 0103-500E</a>	1 ... 2.5 GHz	500 / 600	57 / 62 ±5	2 / 10	3500	4 HU, 730 mm	40
<a href="#">TWAL 0103-1000</a>	1 ... 2.5 GHz	1000 / 1100	50 / 60 ±10	8 / 20	12000	41 HU, 800 mm	340
<a href="#">TWAL 0103-1000E</a>	1 ... 2.5 GHz	1000 / 1100	54 / 61.5 ±7.5	3 / 10	7000	12 HU, 800 mm	100

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0118-20DH (Hybrid)</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	20 / 25 20 / 25	43 / 45 ±2 43 / 48 ±5	20 / 20 5 / 20	500	4 HU, 630 mm	32
<a href="#">TWAL 0118-30/20DH (Hybrid)</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	30 / 35 20 / 25	44.8 / 47 ±2 43 / 48 ±5	20 / 15 5 / 20	500	4 HU, 630 mm	33
<a href="#">TWAL 0118-50DH (Hybrid)</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 14 GHz 14 ... 17 GHz 17 ... 18 GHz	50 / 60 50 / 60 40 / 45 35 / 50	47 / 50 ±3 47 / 52 ±5 46 / 51 ±5 45.4 / 51 ±5	15 / 20 5 / 15 20 / 20 20 / 20	600	4 HU, 630 mm	35
<a href="#">TWAL 0118-100DH (Hybrid)</a>	1 ... 18 GHz 1 ... 6 GHz 6 ... 18 GHz	100 / 120 100 / 120	50 / 53 ±3 50 / 55 ±5	15 / 20 3 / 12	1000	5 HU, 630 mm	54

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0218-20DH (Hybrid)</a>	2 ... 18 GHz 2 ... 6 GHz 6 ... 18 GHz	20 / 25 20 / 25	43 / 45 ±2 43 / 48 ±5	20 / 20 5 / 20	500	4 HU, 630 mm	32

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0204-250E</a>	2 ... 4 GHz	250 / 300	54 / 62 ±7.5	6 / 15	3000	4 HU, 730 mm	32

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0206-200E</a>	2 ... 6 GHz	200 / 220	53 / 60 ±7.5	3 / 10	2500	4 HU, 730 mm	32

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0208-250</a>	2 ... 8 GHz	250 / 300	54 / 62 ±7.5	1 / 5	3000	5 HU, 660 mm	45
<a href="#">TWAL 0208-250E</a>	2.5 ... 8 GHz	250 / 300	54 / 62 ±7.5	3 / 10	2500	4 HU, 630 mm	38
<a href="#">TWAL 0208-300</a>	2 ... 8 GHz	300 / 350	54.8 / 63 ±7.5	0 / 5	3500	5 HU, 660 mm	45
<a href="#">TWAL 0208-500</a>	2.5 ... 7.5 GHz	500 / 550	57 / 62 ±5	5 / 15	3000	4 HU, 630 mm	38
<a href="#">TWAL 0208-500E</a>	2.5 ... 7.5 GHz	500 / 600	57 / 62 ±5	5 / 15	3000	4 HU, 630 mm	30
<a href="#">TWAL 0208-1000</a>	2.5 ... 7.5 GHz	1000 / 1100	60 / 65 ±5	5 / 20	6000	12 HU, 800 mm	100
<a href="#">TWAL 0208-1000E</a>	2.5 ... 7.5 GHz	1000 / 1100	60 / 65 ±5	5 / 20	6000	12 HU, 800 mm	100

Model	Frequency Range	Output Power	Gain min / typ	Harmonics 2nd / 3rd	Line Power	Dimensions (H, D)	Weight
-------	-----------------	--------------	-------------------	------------------------	------------	----------------------	--------

		P <sub>N</sub> min / typ W	dB	dBc	VA	19"-System	kg
<a href="#">TWAL 0408-20</a>	4 ... 8 GHz	20 / 30	43 / 48 ±5	5 / 20	400	3 HU, 550 mm	20
<a href="#">TWAL 0408-250E</a>	4 ... 8 GHz	250 / 300	54 / 62 ±7.5	6 / 15	3000	4 HU, 730 mm	30
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0410-100</a>	4 ... 10 GHz 4 ... 5 GHz 5 ... 10 GHz	70 / 150 150 / 200	50 / 56 ±6 50 / 56 ±6	3 / 10 3 / 10	1500	3 HU, 610 mm	33
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0412-20</a>	4 ... 12 GHz	20 / 40	43 / 51 ±4	0 / 6	500	3 HU, 550 mm	18
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0418-20</a>	4 ... 18 GHz	20 / 40	43 / 48 ±5	0 / 5	500	3 HU, 550 mm	18
<a href="#">TWAL 0418-30E</a>	4 ... 18 GHz 4 ... 4.5 GHz 4.5 ... 6 GHz 6 ... 16 GHz 16 ... 18 GHz	25 / 30 30 / 35 70 / 90 30 / 35	44 / 54 ±10 44.8 / 55 ±10 48.5 / 59 ±10 44.8 / 55 ±10	0 / 1 1 / 1 4 / 15 20 / 20	800	3 HU, 550 mm	16
<a href="#">TWAL 0418-40E</a>	4 ... 18 GHz 4 ... 4.5 GHz 4.5 ... 6 GHz 6 ... 15 GHz 15 ... 18 GHz	30 / 35 40 / 45 70 / 90 40 / 45	44 / 54 ±10 45 / 55 ±10 49 / 59 ±10 45 / 55 ±10	0 / 1 1 / 1 4 / 15 20 / 20	800	3 HU, 550 mm	16
<a href="#">TWAL 0418-50DH (Hybrid)</a>	4 ... 18 GHz 4 ... 6 GHz 6 ... 17 GHz 17 ... 18 GHz	50 / 60 50 / 60 35 / 50	47 / 50 ±3 47 / 52 ±5 45.4 / 51 ±5	20 / 20 5 / 15 20 / 20	800	4 HU, 630 mm	35
<a href="#">TWAL 0418-100E</a>	4 ... 18 GHz 4 ... 4.5 GHz 4.5 ... 18 GHz	80 / 100 100 / 120	50 / 60 ±10 50 / 60 ±10	0 / 3 1 / 10	800	4 HU, 630 mm	20
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0618-20</a>	6 ... 18 GHz	20 / 30	43 / 48 ±5	5 / 20	400	3 HU, 550 mm	20
<a href="#">TWAL 0618-50</a>	6 ... 18 GHz 6 ... 14 GHz 14 ... 18 GHz	50 / 60 40 / 45	47 / 52 ±5 46 / 51 ±5	5 / 15 20 / 20	500	3 HU, 550 mm	22
<a href="#">TWAL 0618-100</a>	6 ... 18 GHz	100 / 120	50 / 53 ±3	3 / 12	700	4 HU, 630 mm	30
<a href="#">TWAL 0618-300</a>	6 ... 18 GHz	300 / 320	54.8 / 60 ±5	5 / 10	2000	3 HU, 630 mm	35
<a href="#">TWAL 0618-300E</a>	6 ... 18 GHz	300 / 320	54.8 / 60 ±5	5 / 10	3000	4 HU, 630 mm	34
<a href="#">TWAL 0618-300L</a>	6 ... 18 GHz	300 / 320	54.8 / 60 ±5	5 / 10	3000	6 HU, 800 mm	47
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0812-20</a>	8 ... 12.4 GHz	20 / 30	43 / 48 ±5	5 / 20	400	3 HU, 550 mm	20
<a href="#">TWAL 0812-1000</a>	8 ... 12.4 GHz	1000 / 1200	60 / 66 ±6	10 / 20	4000	17 HU, 700 mm	98
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 0818-20</a>	8 ... 18 GHz	20 / 30	43 / 53 ±10	12 / 20	400	3 HU, 550 mm	21
<a href="#">TWAL 0818-50/35</a>	8 ... 18 GHz 8 ... 15 GHz 15 ... 18 GHz	50 / 60 35 / 50	47 / 55 ±7.5 43 / 51 ±7.5	5 / 20 5 / 20	400	3 HU, 550 mm	20
<a href="#">TWAL 0818-250</a>	8 ... 18 GHz	250 / 300	54 / 62 ±7.5	8 / 20	1500	3 HU, 630 mm	34
<a href="#">TWAL 0818-250E</a>	8 ... 18 GHz	250 / 300	54 / 62 ±7.5	7 / 15	2000	4 HU, 630 mm	32
<a href="#">TWAL 0818-320</a>	8 ... 18 GHz	320 / 350	55 / 63 ±7.5	6 / 18	1600	3 HU, 630 mm	34
<a href="#">TWAL 0818-500</a>	8 ... 18 GHz	500 / 550	57 / 65 ±7.5	7 / 20	4000	15 HU, 700 mm	115
<a href="#">TWAL 0818-500E</a>	8 ... 18 GHz	500 / 550	57 / 65 ±7.5	7 / 20	3000	8 HU, 630 mm	55
<a href="#">TWAL 0818-1000</a>	8 ... 18 GHz	1000 / 1100	60 / 65 ±5	10 / 20	8000	24 HU, 800 mm	225
<a href="#">TWAL 0818-1000E</a>	8 ... 18 GHz	1000 / 1100	60 / 65 ±5	10 / 20	8000	24 HU, 800 mm	225
<a href="#">TWAL 0818-2000</a>	8 ... 18 GHz	2000 / 2200	63 / 70 ±7.5	10 / 20	16000	41 HU, 800 mm	490
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 1113-400</a>	10.5 ... 13 GHz	400 / 450	46 / 56 ±10	10 / 20	4000	15 HU, 700 mm	90
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 1218-20</a>	12 ... 18 GHz	20 / 40	43 / 48 ±5	5 / 20	400	3 HU, 550 mm	20
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAL 1822-250</a>	18 ... 22 GHz	250 / 300	54 / 57 ±3	20 / 20	3000	5 HU, 660 mm	37
Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg

Model	Frequency Range	Output Power P <sub>N</sub> min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System mm	Weight kg
<b>TWAL 1823-200E</b>	18 ... 23 GHz	200 / 220	53 / 58 ±5	15 / 20	2200	6 HU, 800 mm	35
<b>TWAL 1826-40</b>	18 ... 26.5 GHz	40 / 60	46 / 52 ±6	15 / 20	900	3+3 HU, 630 mm	40
<b>TWAL 1826-40E</b>	18 ... 26.5 GHz	40 / 60	46 / 52 ±6	20 / 20	750	4 HU, 630 mm	35
<b>TWAL 1826-80</b>	18 ... 26.5 GHz	80 / 100	49 / 55 ±6	20 / 20	1800	12 HU, 800 mm	115
<b>TWAL 1826-120</b>	18 ... 26.5 GHz	120 / 150	50.8 / 57 ±6	20 / 20	750	6 HU, 630 mm	38
<b>TWAL 1840-40E</b>	18 ... 40 GHz	40 / 60	46 / 54 ±7.5	7 / 15	700	4 HU, 630 mm	27
<b>TWAL 2640-40</b>	26.5 ... 40 GHz	40 / 60	46 / 52 ±6	20 / 20	900	3+3 HU, 630 mm	40
<b>TWAL 2640-40E</b>	26.5 ... 40 GHz	40 / 60	46 / 52 ±6	20 / 20	750	4 HU, 630 mm	35
<b>TWAL 2640-80</b>	26.5 ... 40 GHz 26.5 ... 38 GHz 38 ... 40 GHz	80 / 100 70 / 80	49 / 55 ±6 48.5 / 55 ±6	20 / 20 20 / 20	1800	12 HU, 630 mm	115
<b>TWAL 2640-120</b>	26.5 ... 40 GHz	120 / 150	50.8 / 57 ±6	20 / 20	750	6 HU, 630 mm	38
<b>TWAL 2731-100E</b>	27 ... 31 GHz	100 / 120	50 / 55 ±5	12 / 15	1250	6 HU, 800 mm	35
<b>TWAL 2731-350</b>	27.5 ... 31 GHz	350 / 500	57 / 62 ±5	12 / 12	1300	6 HU, 630 mm	38
<b>TWAL 4050-40</b>	40 ... 50 GHz	40 / 50	46 / 52 ±6	20 / 20	750	6 HU, 630 mm	38

**EMI Preamplifiers**

Anzahl Modellreihen: 12

Model	Frequency Range	Output Power P <sub>N</sub> min dBm	Gain min / typ dB	Noise Figure dB	Dimensions (W, D, H) mm	Weight kg
<b>BLNA 0110-01N</b>	9 kHz ... 1000 MHz	+8	35 / 36 ±1	1.8	120 x 100 x 51	1.3
<b>BLNA 0125-01N</b>	9 kHz ... 2500 MHz	+8	21 / 22 ±1	7	120 x 100 x 51	1.3
<b>BLNA 0160-01N</b>	10 ... 6000 MHz	0	30 / 32 ±1.5	3	120 x 100 x 51	1.3
<b>BLNA 0160-05N</b>	10 ... 6000 MHz	+10	25 / 30 ±5	5	120 x 100 x 51	1.3
<b>BLNA 0118-01N</b>	10 MHz ... 18 GHz	+20	25 / 27 ±2	4.5	120 x 100 x 51	1.3
<b>BLNA 0320-01N</b>	20 ... 2000 MHz	+8	40 / 41 ±1	3.8	120 x 100 x 51	1.3
<b>BLNA 0360-01N</b>	30 ... 6000 MHz	+5	37 / 39 ±2	2.5	120 x 100 x 51	1.3
<b>BLNA 0360-02N</b>	30 ... 6000 MHz	+10	27 / 30 ±1	1.3	120 x 100 x 51	1.3
<b>BLNA 0130-01N</b>	100 ... 3000 MHz	+10	32 / 35 ±3	1.2	120 x 100 x 51	1.3
<b>BLMA 0118-BT</b>	3 ... 18 GHz <sup>1)</sup>	+8	48 / 51 ±3	3	120 x 100 x 50	1.5
<b>BLMA 0118-M</b>	1 ... 18 GHz	+10	50 / 53 ±3	2.3	120 x 100 x 50	1.5
<b>BLMA 0118-1A</b>	1 ... 18 GHz	+10	30 / 32 ±2	2.5	120 x 100 x 50	1.5
<b>BLMA 0118-1ABT</b>	3 ... 18 GHz <sup>1)</sup>	+9	28 / 30 ±2	3.3	120 x 100 x 50	1.5
<b>BLMA 0118-1BT</b>	3 ... 18 GHz <sup>1)</sup>	+9	36 / 39 ±3	3.2	120 x 100 x 50	1.5
<b>BLMA 0118-1M</b>	1 ... 18 GHz	+10	38 / 41 ±3	2.5	120 x 100 x 50	1.5
<b>BLMA 0118-3A</b>	1 ... 18 GHz	+10	30 / 32 ±2	3	120 x 100 x 50	1.5
<b>BLMA 0118-4A</b>	1 ... 18 GHz	+10	36 / 38 ±2	3	120 x 100 x 50	1.5
<b>BLMA 0118-5A</b>	1 ... 18 GHz	+10	48 / 50 ±2	3	120 x 100 x 50	1.5
<b>BLMA 0118-3G</b>	1 ... 18 GHz	+10	30 / 32 ±2	3.5	120 x 100 x 50	1.5
<b>BLMA 0118-4G</b>	1 ... 18 GHz	+8	40 / 42 ±2	3.5	120 x 100 x 50	1.5
<b>BLMA 0118-5G</b>	1 ... 18 GHz	+8	49 / 51 ±2	3.5	120 x 100 x 50	1.5

		$P_N$ min dBm	min / typ dB	dB	(W, D, H) mm	kg
<a href="#">BLMA 0126-2M</a>	1 ... 26.5 GHz	+10	30 / 32 ±2	4	133 x 80 x 52	1
Model	Frequency Range	Output Power $P_N$ min dBm	Gain min / typ dB	Noise Figure dB	Dimensions (W, D, H) mm	Weight kg
<a href="#">BLMA 1826-1M</a>	18 ... 26.5 GHz	+10	40 / 42 ±2	2.5	144 x 93 x 65	1
<a href="#">BLMA 1826-2M</a>	18 ... 26.5 GHz	+10	30 / 32 ±2	2.5	144 x 93 x 65	1
<a href="#">BLMA 1826-3A</a>	18 ... 26.5 GHz	+10	30 / 32 ±2	3	144 x 93 x 65	1
<a href="#">BLMA 1826-4A</a>	18 ... 26.5 GHz	+10	38 / 40 ±2	3	144 x 93 x 65	1
<a href="#">BLMA 1826-4M</a>	18 ... 26.5 GHz	+10	42 / 44 ±2	1.8	144 x 93 x 65	1
<a href="#">BLMA 1826-5A</a>	18 ... 26.5 GHz	+10	50 / 52 ±2	3	144 x 93 x 65	1
Model	Frequency Range	Output Power $P_N$ min dBm	Gain min / typ dB	Noise Figure dB	Dimensions (W, D, H) mm	Weight kg
<a href="#">BLMA 1840-1M</a>	18 ... 40 GHz	+5	23 / 26 ±2.5	2.7	120 x 100 x 51	1
<a href="#">BLMA 1840-1A</a>	18 ... 40 GHz	+5	23 / 26 ±2.5	3	120 x 100 x 51	1
<a href="#">BLMA 1840-2A</a>	18 ... 40 GHz	+5	23 / 26 ±2.5	3.5	120 x 100 x 51	1
<a href="#">BLMA 1840-3A</a>	18 ... 40 GHz	+5	23 / 26 ±2.5	5	120 x 100 x 51	1
<a href="#">BLMA 1840-3G</a>	18 ... 40 GHz	+5	30 / 33 ±2.5	2.9	120 x 100 x 51	1
<a href="#">BLMA 1840-4G</a>	18 ... 40 GHz	+5	40 / 43 ±2.5	3.5	120 x 100 x 51	1
<a href="#">BLMA 1840-4A</a>	18 ... 40 GHz	+5	32 / 35 ±2.5	2.8	120 x 100 x 51	1
Model	Frequency Range	Output Power $P_N$ min dBm	Gain min / typ dB	Noise Figure dB	Dimensions (W, D, H) mm	Weight kg
<a href="#">BLMA 2640-1M</a>	26.5 ... 40 GHz	+10	38 / 41 ±3	2.8	161 x 93 x 65	1
<a href="#">BLMA 2640-3F</a>	26.5 ... 40 GHz	+8	30 / 33 ±3	3	161 x 93 x 65	1
<a href="#">BLMA 2640-3A</a>	26.5 ... 40 GHz	+10	30 / 33 ±3	4	161 x 93 x 65	1
<a href="#">BLMA 2640-4A</a>	26.5 ... 40 GHz	+10	40 / 43 ±3	3.5	161 x 93 x 65	1
<a href="#">BLMA 2640-5A</a>	26.5 ... 40 GHz	+10	48 / 52 ±4	4	161 x 93 x 65	1
<a href="#">BLMA 2640-5F</a>	26.5 ... 40 GHz	+8	47 / 50 ±3	3	161 x 93 x 65	1

**BPA**

Anzahl Modellreihen: 13

Model	Frequency Range	Output Power $P_P$ min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 3050-50</a>	300 ... 500 MHz	50 / 10	100 µs	47 ±1.5	20 / 20	80	2 HU, 430 mm	25
<a href="#">BPA 3050-100</a>	300 ... 500 MHz	100 / 10	100 µs	50 ±1.5	20 / 20	150	2 HU, 430 mm	25
<a href="#">BPA 3050-250</a>	300 ... 500 MHz	250 / 10	100 µs	54 ±1.5	20 / 20	250	4 HU, 630 mm	30
<a href="#">BPA 3050-500</a>	300 ... 500 MHz	500 / 10	100 µs	57 ±1.5	20 / 20	350	4 HU, 630 mm	40
<a href="#">BPA 3050-1000</a>	300 ... 500 MHz	1000 / 10	100 µs	60 ±1.5	20 / 20	500	4 HU, 630 mm	45
<a href="#">BPA 3050-2000</a>	300 ... 500 MHz	2000 / 10	100 µs	63 ±1.5	20 / 20	750	6 HU, 630 mm	55
<a href="#">BPA 3050-4000</a>	300 ... 500 MHz	4000 / 10	100 µs	66 ±1.5	20 / 20	1000	7 HU, 630 mm	75
<a href="#">BPA 3050-7000</a>	300 ... 500 MHz	7000 / 10	100 µs	68 ±1.5	20 / 20	2000	12 HU, 800 mm	115
Model	Frequency Range	Output Power $P_P$ min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 4010-1000</a>	400 ... 1000 MHz	1000 / 10	100 µs	60 ±2	15 / 20	900	3 HU, 630 mm	32
<a href="#">BPA 4010-1200</a>	400 ... 1000 MHz	1200 / 10	100 µs	61 ±2	15 / 20	1000	5 HU, 630 mm	55
<a href="#">BPA 4010-2000</a>	400 ... 1000 MHz	2000 / 10	100 µs	63 ±2	15 / 20	2000	9 HU, 630 mm	90
<a href="#">BPA 4010-4000</a>	400 ... 1000 MHz	4000 / 10	100 µs	66 ±2	20 / 20	4000	12 HU, 630 mm	155
<a href="#">BPA 4010-10000</a>	400 ... 1000 MHz	10000 / 4	40 µs	70 ±2	15 / 20	4500	24 HU, 800 mm	300
Model	Frequency Range	Output Power $P_P$ min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 4020-1000</a>	400 ... 2000 MHz	1000 / 10	100 µs	60 ±3	15 / 15	1700	4 HU, 630 mm	37
Model	Frequency Range	Output Power $P_P$ min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 0913-100</a>	950 ... 1250 MHz	100 / 5	100 µs	50 ±2.5	40 / 40	300	2 HU, 430 mm	15
<a href="#">BPA 0913-500</a>	950 ... 1250 MHz	500 / 5	100 µs	57 ±2.5	40 / 40	300	3 HU, 630 mm	25
<a href="#">BPA 0913-1000</a>	950 ... 1250 MHz	1000 / 5	2 µs	60 ±2.5	30 / 30	1400	3 HU, 630 mm	21
<a href="#">BPA 0913-2500</a>	950 ... 1250 MHz	2500 / 10	100 µs	64 ±2	30 / 30	2100	4 HU, 630 mm	34
<a href="#">BPA 0913-4000</a>	950 ... 1250 MHz	4000 / 5	100 µs	66 ±2.5	40 / 40	1200	12 HU, 800 mm	120
<a href="#">BPA 0913-7500</a>	950 ... 1250 MHz	7500 / 5	100 µs	68 ±2.5	40 / 40	2500	24 HU, 800 mm	220
Model	Frequency Range	Output Power $P_P$ min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 1000-2000</a>	995 ... 1003 MHz	2000 / 1	50 µs	63 ±0.5	30 / 50	300	3 HU, 630 mm	25
Model	Frequency Range	Output Power $P_P$ min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 1020-1000</a>	1 ... 2 GHz	1000 / 10	100 µs	60 ±3	15 / 15	900	4 HU, 630 mm	37
<a href="#">BPA 1020-2000</a>	1 ... 2 GHz	2000 / 10	100 µs	63 ±3	15 / 15	2000	8 HU, 630 mm	82
<a href="#">BPA 1020-4000</a>	1 ... 2 GHz	4000 / 10	100 µs	66 ±3	12 / 20	4000	12 HU, 800 mm	150
<a href="#">BPA 1020-8000</a>	1 ... 2 GHz	8000 / 10	100 µs	69 ±3	12 / 20	7500	21 HU, 800 mm	220
<a href="#">BPA 1020-11000</a>	1 ... 2 GHz	11000 / 10	100 µs	70.4 ±3	10 / 20	12000	32 HU, 800 mm	450

Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 1025-1000</a>	1 ... 2.5 GHz	1000 / 10	100 µs	60 ±3	15 / 15	900	4 HU, 630 mm	37
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 1114-900</a>	1.2 ... 1.5 GHz	900 / 10	100 µs	62 ±2.5	30 / 30	500	3 HU, 630 mm	22
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 1214-500</a>	1.2 ... 1.4 GHz	500 / 10	100 µs	57 ±2.5	30 / 30	250	2 HU, 430 mm	14
<a href="#">BPA 1214-1000</a>	1.2 ... 1.4 GHz	1000 / 10	100 µs	60 ±2.5	30 / 30	500	3 HU, 630 mm	22
<a href="#">BPA 1214-1800</a>	1.2 ... 1.4 GHz	1800 / 10	100 µs	63 ±2.5	30 / 30	1000	4 HU, 630 mm	35
<a href="#">BPA 1214-3000</a>	1.2 ... 1.4 GHz	3000 / 10	100 µs	65 ±2.5	30 / 30	1500	6 HU, 630 mm	35
<a href="#">BPA 1214-5000</a>	1.2 ... 1.4 GHz	5000 / 10	100 µs	67 ±2.5	30 / 30	3000	8 HU, 630 mm	60
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 1231-1000/500DP1</a>	1.2 ... 3.1 GHz 1.2 ... 1.4 GHz 2.7 ... 3.1 GHz	1000 / 1 500 / 1	10 µs 10 µs	60 ±2 57 ±2	30 / 30 30 / 30	1200	4 HU, 630 mm	32

Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 2427-25</a>	2.4 ... 2.7 GHz	25 / 10	100 µs	44 ±2.5	40 / 40	125	2 HU, 430 mm	15
<a href="#">BPA 2427-50</a>	2.4 ... 2.7 GHz	50 / 10	100 µs	47 ±2.5	40 / 40	200	2 HU, 430 mm	15
<a href="#">BPA 2427-100</a>	2.4 ... 2.7 GHz	100 / 10	100 µs	50 ±2.5	40 / 40	350	2 HU, 430 mm	15
<a href="#">BPA 2427-500</a>	2.4 ... 2.7 GHz	500 / 10	100 µs	57 ±2.5	40 / 40	1000	4 HU, 630 mm	25
<a href="#">BPA 2427-1000</a>	2.4 ... 2.7 GHz	1000 / 10	100 µs	60 ±2.5	40 / 40	1700	4 HU, 630 mm	30
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 2731-50</a>	2.7 ... 3.1 GHz	50 / 10	100 µs	47 ±2.5	30 / 30	150	2 HU, 430 mm	15
<a href="#">BPA 2731-100</a>	2.7 ... 3.1 GHz	100 / 10	100 µs	50 ±2.5	30 / 30	250	3 HU, 430 mm	15
<a href="#">BPA 2731-200</a>	2.7 ... 3.1 GHz	200 / 10	100 µs	53 ±2.5	30 / 30	250	3 HU, 630 mm	20
<a href="#">BPA 2731-300</a>	2.7 ... 3.1 GHz	300 / 10	100 µs	55 ±2.5	30 / 30	300	3 HU, 630 mm	21
<a href="#">BPA 2731-400</a>	2.7 ... 3.1 GHz	400 / 10	100 µs	56 ±2.5	30 / 30	350	3 HU, 630 mm	22
<a href="#">BPA 2731-500</a>	2.7 ... 3.1 GHz	500 / 10	100 µs	57 ±2.5	40 / 40	500	4 HU, 630 mm	28
<a href="#">BPA 2731-1000</a>	2.7 ... 3.1 GHz	1000 / 10	100 µs	60 ±2.5	40 / 40	1000	4 HU, 630 mm	30
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W pk / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">BPA 7510-500</a>	7.5 ... 10 GHz	500 / 1	100 µs	57 ±2	30 / 30	1700	5 HU, 630 mm	46

## TWAP

Anzahl Modellreihen: 16

Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0115-8000</a>	1 ... 1.5 GHz	8000 / 4	50 µs	75 ±5	20 / 20	2000	4 HU, 730 mm	38
<a href="#">TWAP 0115-10000</a>	1 ... 1.5 GHz	10000 / 2	50 µs	75 ±5	20 / 20	1500	4 HU, 730 mm	38
<a href="#">TWAP 0115-12000</a>	1 ... 1.5 GHz	12000 / 1	50 µs	75 ±5	20 / 20	1200	4 HU, 730 mm	38
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0102-4000</a>	1 ... 2 GHz	4000 / 4	50 µs	71 ±5	6 / 10	2500	5 HU, 630 mm	60
<a href="#">TWAP 0102-4000L</a>	1 ... 2 GHz	4000 / 4	50 µs	71 ±5	6 / 10	2500	6 HU, 800 mm	45
<a href="#">TWAP 0102-7000</a>	1 ... 2 GHz	7000 / 4	50 µs	73.5 ±7.5	6 / 10	5000	18 HU, 800 mm	150
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0103-2000</a>	1 ... 2.5 GHz	2000 / 6	50 µs	70.5 ±7.5	7 / 15	1200	4 HU, 730 mm	42
<a href="#">TWAP 0103-2000L</a>	1 ... 2.5 GHz	2000 / 6	50 µs	70.5 ±7.5	7 / 15	1200	6 HU, 800 mm	48
<a href="#">TWAP 0103-3500</a>	1 ... 2.5 GHz	3500 / 6	50 µs	72 ±7.5	7 / 15	2500	12 HU, 800 mm	125
<a href="#">TWAP 0103-6000</a>	1 ... 2.5 GHz	6000 / 6	50 µs	74 ±7.5	7 / 15	5000	24 HU, 800 mm	250
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 1113-20000</a>	1.1 ... 1.3 GHz	20000 / 2	50 µs	80 ±7.5	20 / 20	2750	12 HU, 800 mm	115
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 1115-2000</a>	1.1 ... 1.5 GHz	2000 / 4	50 µs	71 ±7.5	20 / 20	1000	4 HU, 830 mm	40
<a href="#">TWAP 1115-30000</a>	1.1 ... 1.5 GHz	30000 / 1	50 µs	83 ±7.5	17 / 20	4000	8 HU, 1200 mm	80
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 1502-6000</a>	1.5 ... 2 GHz	6000 / 4	50 µs	75 ±5	20 / 20	2000	4 HU, 730 mm	38
<a href="#">TWAP 1502-8000</a>	1.5 ... 2 GHz	8000 / 2	50 µs	75 ±5	20 / 20	1500	4 HU, 730 mm	38

<a href="#">TWAP 1502-10000</a>	1.5 ... 2 GHz	10000 / 1	50 µs	75 ±5	20 / 20	1200	4 HU, 830 mm	38
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0203-7500</a>	2.7 ... 3.3 GHz	7500 / 6	50 µs	73 ±5	20 / 20	1000	4 HU, 730 mm	45
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0204-2000</a>	2 ... 4 GHz	2000 / 6	50 µs	71 ±7.5	4 / 10	1200	4 HU, 730 mm	35
<a href="#">TWAP 0204-5000</a>	2 ... 4 GHz	5000 / 6	50 µs	75 ±7.5	3 / 8	2800	4 HU, 730 mm	39
<a href="#">TWAP 0204-5000L</a>	2 ... 4 GHz	5000 / 6	50 µs	75 ±7.5	3 / 8	2800	6 HU, 800 mm	48
<a href="#">TWAP 0204-9000</a>	2 ... 4 GHz	9000 / 6	50 µs	78 ±7.5	7 / 12	6000	12 HU, 800 mm	100
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0208-1500</a>	2 ... 8 GHz	1500 / 6	50 µs	70 ±7.5	2 / 2	1100	4 HU, 630 mm	33
<a href="#">TWAP 0208-2000</a>	2 ... 8 GHz	2000 / 6	50 µs	71 ±7.5	2 / 10	1200	4 HU, 730 mm	35
<a href="#">TWAP 0208-2000L</a>	2 ... 8 GHz	2000 / 6	50 µs	71 ±7.5	2 / 10	1200	6 HU, 800 mm	48
<a href="#">TWAP 0208-3000</a>	2 ... 8 GHz	3000 / 6	50 µs	74 ±7.5	10 / 10	2400	12 HU, 800 mm	80
<a href="#">TWAP 0208-4000</a>	2 ... 8 GHz	4000 / 6	50 µs	74 ±7.5	0 / 0	1500	8 HU, 630 mm	50
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0304-9000</a>	2.9 ... 4 GHz	9000 / 4	50 µs	77.5 ±7.5	6 / 15	2000	4 HU, 730 mm	35
<a href="#">TWAP 0304-9000L</a>	2.9 ... 4 GHz	9000 / 4	50 µs	77.5 ±7.5	6 / 15	2000	6 HU, 800 mm	48
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0408-1800</a>	4 ... 8 GHz	1800 / 6	50 µs	70 ±7.5	7 / 12	1200	4 HU, 630 mm	35
<a href="#">TWAP 0408-4000</a>	4 ... 8 GHz	4000 / 6	50 µs	70 ±4	5 / 20	1600	6 HU, 630 mm	40
<a href="#">TWAP 0408-4000L</a>	4 ... 8 GHz	4000 / 6	50 µs	70 ±4	5 / 20	1600	6 HU, 800 mm	48
<a href="#">TWAP 0408-7500</a>	4 ... 8 GHz	7500 / 6	50 µs	73 ±4	5 / 20	3500	12 HU, 800 mm	100
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0811-7000</a>	8.5 ... 10.5 GHz	7000 / 5	50 µs	83.5 ±7.5	8 / 15	2000	4 HU, 730 mm	38
<a href="#">TWAP 0811-7000L</a>	8.5 ... 10.5 GHz	7000 / 5	50 µs	83.5 ±7.5	8 / 15	2000	6 HU, 800 mm	48
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0812-2500</a>	8 ... 12.4 GHz	2500 / 6	50 µs	72 ±7.5	10 / 15	1500	4 HU, 630 mm	35
<a href="#">TWAP 0812-2500L</a>	8 ... 12.4 GHz	2500 / 6	50 µs	72 ±7.5	10 / 15	1500	6 HU, 800 mm	48
<a href="#">TWAP 0812-4000L</a>	8 ... 12.4 GHz	4000 / 6	50 µs	72 ±5	10 / 20	1600	6 HU, 800 mm	48
<a href="#">TWAP 0812-5000</a>	8 ... 12 GHz	5000 / 6	50 µs	72 ±5	10 / 20	1600	4 HU, 630 mm	35
<a href="#">TWAP 0812-5000L</a>	8 ... 12 GHz	4000 / 6	50 µs	71 ±5	20 / 20	1600	6 HU, 630 mm	48
<a href="#">TWAP 0812-8000</a>	8 ... 12.4 GHz	8000 / 6	50 µs	77 ±7.5	15 / 20	4000	12 HU, 800 mm	100
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0818-1800</a>	8 ... 18 GHz	1800 / 6	50 µs	68 ±5	7 / 20	1300	4 HU, 630 mm	33
<a href="#">TWAP 0818-1800L</a>	8 ... 18 GHz	1800 / 6	50 µs	68 ±5	7 / 20	1300	6 HU, 800 mm	48
<a href="#">TWAP 0818-2000</a>	8 ... 18 GHz	2000 / 6	50 µs	68 ±6	7 / 20	1300	4 HU, 630 mm	33
<a href="#">TWAP 0818-2000L</a>	8 ... 18 GHz	2000 / 6	50 µs	68 ±6	7 / 20	1300	6 HU, 800 mm	48
<a href="#">TWAP 0818-2500</a>	8 ... 18 GHz	2500 / 6	50 µs	72 ±7.5	7 / 15	2000	8 HU, 630 mm	50
<a href="#">TWAP 0818-3000</a>	8 ... 18 GHz	3000 / 6	50 µs	74 ±7.5	8 / 10	3000	12 HU, 800 mm	108
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 0910-8000</a>	9.2 ... 10 GHz	8000 / 5	50 µs	68 ±5	10 / 20	2000	6 HU, 800 mm	48
Model	Frequency Range	Output Power P <sub>P</sub> min / Duty W / %	Pulse Width max. **)	Gain typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
<a href="#">TWAP 1218-3500</a>	12.4 ... 18 GHz	3500 / 6	50 µs	71 ±5	15 / 15	1500	4 HU, 630 mm	35
<a href="#">TWAP 1218-3500L</a>	12.4 ... 18 GHz	3500 / 6	50 µs	71 ±5	15 / 15	1500	6 HU, 800 mm	48
<a href="#">TWAP 1218-6000</a>	12.4 ... 18 GHz	6000 / 6	50 µs	73 ±5	20 / 20	3000	12 HU, 800 mm	100

Number of Models: 1041